

These tables contain the result codes returned by the routines described in *Inside Macintosh*. Table 1 lists the result codes alphabetically by their constants; Table 2 on page 35 lists the result codes according to their values.

Table 1 Result codes (in alphabetic order)

[no name]	-143	CopyBits couldn't allocate required temporary memory
[no name]	-144	Ran out of stack space while drawing polygon
[no name]	-8131	Printer not responding
[no name]	1	User canceled initializing
[no name]	2	Disk in specified drive is already mounted
abortErr	-27	Asynchronous recording was cancelled; publisher has written a new edition; request aborted by KillIO
about_to_grow_heap	-26995	
about_to_unload_objects	-26994	
addResFailed	-194	AddResource procedure failed
afpAccessDenied	-5000	The operation has failed because the user does not have the correct access to the file or folder
afpAlreadyMounted	-5062	Volume already mounted
afpBadDirIDType	-5060	Not a fixed directory ID volume
afpBadIDErr	-5039	Bad file ID
afpBadUAM	-5002	User authentication method is unknown
afpBadVersNum	-5003	Workstation is using an AFP version that the server doesn't recognize
afpCantMountMoreSrvrs	-5061	Maximum number of volumes have been mounted
afpCatalogChanged	-5037	Catalog has changed and search cannot be resumed
afpContainsSharedErr	-5033	The directory contains a share point
afpDenyConflict	-5006	The operation has failed because the permission or deny mode conflicts with the mode in which the fork has already been opened
afpIconTypeError	-5030	Sizes of new icon and one it replaces don't match
afpIDExists	-5035	File ID already exists
afpIDNotFound	-5034	File ID not found
afpInsideSharedErr	-5043	The directory is inside a shared directory
afpItemNotFound	-5012	Could not determine kind string; application information not found
afpNoMoreLocks	-5015	Byte range locking has failed because the server cannot lock any additional ranges
afpNoServer	-5016	Server is not responding
afpObjectTypeErr	-5025	Object is a directory, not a file; a directory exists with that name; this directory is not a share point
afpParmError	-5019	The AFP command block size is equal to 0 (this error is also returned when the command block is equal to 0 or \$FF [255] or GetSrvrStatus [15])
afpPwdExpired	-5042	Password has expired on server
afpRangeNotLocked	-5020	User has attempted to unlock a range that was not locked by that user
afpRangeOverlap	-5021	User attempted to lock some or all of a range that is already locked
afpSameNodeErr	-5063	Attempt to log on to a server running on the same machine
afpSameObjectErr	-5038	Source and destination files are the same
afpUserNotAuth	-5023	User authentication failed (usually, password is not correct)

appIsDaemon	-606	Application is background-only
appMemFullErr	-605	Partition size specified in 'SIZE' resource is not big enough for launch
appModeErr	-602	Addressing mode is 32-bit, but application is not 32-bit clean
aspBadVersNum	-1066	The server cannot support the ASP version number
aspBufTooSmall	-1067	
aspNoMoreSess	-1068	
aspNoServers	-1069	
aspParamErr	-1070	
aspServerBusy	-1071	
aspSessClosed	-1072	The .XPP driver is in the process of closing the session
aspSizeErr	-1073	The size of the command block exceeds the maximum size of aspMaxCmdSize
attributes_already_set	-25998	
authFailErr	-927	User's password is wrong
backing_free_parent_mismatch	-27508	
backing_store_parent_mismatch	-27507	
bad_address	-27585	
badATPSkt	-1099	Bad responding socket
badBuffNum	-1100	Sequence number out of range
badChannel	-205	Channel is corrupt or unusable
badComponentInstance	\$800008001	Invalid component passed to Component Manager; invalid component instance
badComponentSelector	\$800008002	Component does not support the specified request code
badComponentType	-2005	Component cannot accommodate this data
badControllerHeight	-9994	Invalid height
bad_data_in_stream	-26840	
badDataRefIndex	-2050	Data reference index value is invalid
bad_device_attributes	-27520	
bad_device_private_flags	-27521	
badDictFormat	-246	Pronunciation dictionary format error
badEditIndex	-2033	This edit index value is not valid
badEditList	-2017	The track's edit list is corrupted
badFileFormat	-208	File is corrupt or unusable, or not AIFF or AIFF-C
bad_fillType_in_textFace	-27542	
badFormat	-206	Resource is corrupt or unusable
badImageDescription	-2001	Problem with this image description
bad_ink_in_picture	-27548	
badLocNameErr	-931	Location name is invalid
badMDBErr	-60	Bad master directory block
badMovErr	-122	Attempted to move into offspring
badParmCount	-252	Incorrect number of embedded command arguments
badPhonemeText	-247	Raw phoneme text contains invalid characters
badPortNameErr	-919	PPC port record is invalid
bad_printer_flags	-27578	
badPublicMovieAtom	-2002	Movie file corrupted
badReqErr	-909	Bad parameter or invalid state for this operation

badSectionErr	-451	Not a valid section type
bad_seed_in_picture	-27545	
badServiceMethodErr	-930	Service method is other than ppcServiceRealTime
bad_shape_cache_in_picture	-27546	
bad_shape_in_picture	-27550	
bad_style_in_picture	-27549	
bad_style_in_textFace	-27541	
badSubPartErr	-454	Bad edition container spec or invalid edition container
bad_textLayer_count	-27543	
badTrackIndex	-2028	This track index value is not valid
bad_transform_in_picture	-27547	
bad_transform_in_textFace	-27540	
badTranslationSpecErr	-3031	Translation path is invalid
badUnitErr	-21	Driver reference number does not match unit table
badVoiceID	-250	Specified voice has not been preloaded
bdNamErr	-37	Bad filename or volume name (perhaps zero length)
bitmap_colorSet_one_entry	33	The bitmap drew, but it is probably not the desired result, since all colors map to the one color of the entry—an example is when the colors are off the end of the color set
bitmap_height_negative	-27571	
bitmap_is_not_resizable	-27639	
bitmap_pixel_size_must_be_1	-27668	
bitmap_ptr_not_aligned	-27574	
bitmap_ptr_too_small	-27575	
bitmap_rowBytes_must_be_specified_for_user_image_buffer	-27567	
bitmap_rowBytes_negative	-27573	
bitmap_rowBytes_not_aligned	-27568	
bitmap_rowBytes_too_small	-27569	
bitmap_width_negative	-27572	
bitmap_zero_height	8	The bitmap doesn't have an area to draw
bitmap_zero_width	7	The bitmap doesn't have an area to draw
btDupRecErr	-414	Record already exists
btKeyLenErr	-416	Key length too great or equal to zero
btNoSpace	-413	Insufficient disk space to store dictionary
btRecNotFnd	-415	Record cannot be found
buf2SmallErr	-3101	Packet too large for buffer; partial data returned
bufferIsSmall	-607	Buffer is too small
buffersTooSmall	-210	Buffer is too small
bufTooSmall	-243	Output buffer is too small to hold result
cache_already_cleared	-25952	
cannot_add_unspecified_new_glyphs	-27660	
cannotDeferErr	-625	Unable to defer additional user functions
cannot_dispose_default_colorProfile	-26689	

cannot_dispose_default_colorSet	-26688	
cannot_dispose_default_ink	-26691	
cannot_dispose_default_shape	-26693	
cannot_dispose_default_style	-26692	
cannot_dispose_default_transform	-26690	
cannot_dispose_locked_shape	-27658	
cannot_dispose_locked_tag	-27659	
cannot_dispose_non_font	-26685	
cannotMakeContiguousErr	-622	Cannot make specified range contiguous
cannotMoveAttachedController	-9999	Cannot move attached controllers
cannot_set_graphics_client_memory_without_setting_size	-27647	
cannot_set_item_shapes_to_nil	-27662	
cannot_set_unique_items_attribute_when_picture_contains_items	-27619	
cannotSetWidthOfAttachedController	-9997	Cannot change controller width
cannot_use_original_item_shapes_when_growing_picture	-27661	
cantCreateSingleForkFile	-2022	Error trying to create a single-fork file—this occurs when the file already exists
cantEnableTrack	-2035	Cannot enable this track
cantFindHandler	-2003	Cannot locate this handler
cantLoadPickMethodErr	-11003	Custom pick method not in resource chain
cantOpenHandler	-2004	Cannot open this handler
cantPutPublicMovieAtom	-2016	Cannot write to this movie file
caps_already_set	-25997	
catChangedErr	-1304	Catalog has changed and catalog position record may be invalid
cbNotFound	-1102	ERead not active; NBP queue element not found; the aKillQEl parameter does not point to a PSendRequest or PNSendRequest queue element
cDepthErr	-157	Invalid pixel depth
cDevErr	-155	Invalid type of graphics device
channelBusy	-209	Channel is busy
channelNotBusy	-211	Channel not currently used
character_substitution_took_place	-26845	
clip_already_set	-25996	
clip_to_frame_shape_unimplemented	-27699	
clkRdErr	-85	Unable to read clock
clkWrErr	-86	Time written did not verify
closErr	-24	Driver unable to complete close request

cMatchErr	-150	Color2Index failed to find an index
cNoMemErr	-152	Failed to allocate memory for structure
codecAbortErr	-8967	Operation aborted by the progress function
codecBadDataErr	-8969	Compressed data contains inconsistencies
codecConditionErr	-8972	Component cannot perform requested operation
codecDataVersErr	-8970	Compressor does not support the compression version used to compress the image
codecErr	-8960	General error returned by compressor; can be returned by any function that gets handled by the compressor
codecExtensionNotFoundErr	-8971	Requested extension is not in the image description structure
codecImageBufErr	-8965	Could not allocate the image buffer
codecOpenErr	-8973	Compressor or decompressor component could not be opened by the Image Compression Manager
codecScreenBufErr	-8964	Could not allocate the screen buffer
codecSizeErr	-8963	Invalid buffer size specified
codecSpoolErr	-8966	Error loading or unloading data
codecUnimpErr	-8962	Feature not implemented by this compressor
codecWouldOffScreenErr	-8968	Compressor would use screen buffer if it could
color_already_set	-25995	
color_index_requested_not_found	-26897	
color_is_nil	-27844	
colorProfile_access_restricted	-27655	
colorProfile_is_nil	-27843	
colorProfile_must_be_nil	-27669	
colorProfile_not_disposed	-25946	
colorProfile_wrong_type	-27511	
colorSet_access_restricted	-27656	
colorSet_index_out_of_range	-26896	
colorSet_is_nil	-27842	
colorSet_no_entries	32	There are no colors in the color set so there is nothing to draw
colorSet_not_disposed	-25947	
colorSet_wrong_type	-27515	
colorSpace_out_of_range	-27684	
colorsRequestedErr	-11004	Number out of range or greater than that passed to NewPictInfo
complex_glyph_style_not_allowed	-27664	
componentNotCaptured	-3002	This component has not been captured
connectionInvalid	-609	Connection is invalid; nonexistent signature or session ID
containerNotFoundWrn	-461	Alias was not resolved
contour_is_less_than_zero	-27689	
contour_out_of_range	-26900	

controlErr	-17	Driver does not respond to this control request; unimplemented control instructions—the Device Manager returns this result code
controllerBoundsNotExact	-9996	Boundary rectangle not exact
controllerHasFixedHeight	-9998	Cannot change controller height
corErr	-3	PowerShare mail server not running
could_not_create_backing_store	-27995	
could_not_dispose_backing_store	-27946	
couldNotResolveDataRef	-2000	Cannot use this data reference
couldNotUseAnExistingSample	-2052	Movie Toolbox could not use a sample
count_is_less_than_one	-27690	
count_is_less_than_zero	-27691	
count_out_of_range	-26894	
cProtectErr	-154	ColorTable record entry protection violation
cRangeErr	-153	Range error on color table request
cResErr	-156	Invalid resolution for MakeITable
cTempMemErr	-151	Failed to allocate memory for temporary structures
curve_error_already_set	-25994	
dash_already_set	-25993	
dash_empty	21	The dash shape was specified as an empty type shape
dataAlreadyClosed	-2045	You have already closed this data source
dataAlreadyOpenForWrite	-2044	Data source is already open for write
dataNoDataRef	-2047	No data reference value found
dataNotOpenForRead	-2042	Cannot read from this data source
dataNotOpenForWrite	-2043	Cannot write to this data source
ddpLenErr	-92	Datagram is too long
ddpSktErr	-91	Error opening socket; bad socket number or socket table is full
default_colorProfile_already_set	-25992	
default_ink_already_set	-25991	
default_shape_already_set	-25989	
default_style_already_set	-25988	
default_transform_already_set	-25990	
desktopDamagedErr	-1305	The desktop database has become corrupted—the Finder will fix this, but if your application is not running with the Finder, use PBDTRreset or PBDTDelete
destPortErr	-906	Port does not exist at destination; server hasn't set 'SIZE' resource to indicate awareness of high-level events, or else is not present
device_wrong_type	-27611	
diffVolErr	-1303	Files are on different volumes
dInstErr	-26	Driver resource not found
directShape_attribute_set_as_side_effect	-25941	
dirFulErr	-33	File directory full

dirNFErr	-120	Directory not found or incomplete pathname
disposed_dead_caches	-25935	
disposed_live_caches	-25934	
dither_already_set	-25987	
dRemovErr	-25	Attempt to remove an open driver
dskFulErr	-34	All allocation blocks on the volume are full; not enough disk space to translate file
dupFNErr	-48	A file with the specified name already exists; file found instead of folder
editingNotAllowed	-9995	Controller does not support editing
editionMgrInitErr	-450	Manager not initialized or could not load package
eLenErr	-92	Packet too large or first entry of the write-data structure did not contain the full 14-byte header
empty_shape_not_allowed	-27667	
eMultiErr	-91	Address not found
encoding_already_set	-25986	
endOfDataReached	-2046	End of data
envBadVers	-5501	Nonpositive version number passed
envNotPresent	-5500	SysEnviron trap not present
envVersTooBig	-5502	Requested version of SysEnviron not available
eofErr	-39	Logical end-of-file reached; no additional data in the format
errAborted	-1279	Request aborted by dspRemove or dspClose routine
errADBop	-1	Unsuccessful completion
errAEAccessorNotFound	-1723	There is no object accessor function for the specified object class and token descriptor type
errAEBadTestKey	-1726	The descriptor record in a test key is neither a comparison descriptor record nor a logical descriptor record
errAECoercionFail	-1700	Data could not be coerced to the requested descriptor type
errAECorruptData	-1702	Data in an Apple event could not be read
errAEDescNotFound	-1701	Descriptor record was not found
errAEEEmptyListContainer	-1730	The container for an Apple event object is specified by an empty list
errAEEEventNotHandled	-1708	Event wasn't handled by an Apple event handler
errAEHandlerNotFound	-1717	No handler found for an Apple event or a coercion, or no object callback function found
errAEIllegalIndex	-1719	Not a valid list index
errAEImpossibleRange	-1720	The range is not valid because it is impossible for a range to include the first and last objects that were specified; an example is a range in which the offset of the first object is greater than the offset of the last object
errAENegativeCount	-1729	Object-counting function returned negative value
errAENewerVersion	-1706	Need a newer version of the Apple Event Manager
errAENoSuchLogical	-1725	The logical operator in a logical descriptor record is not kAEAND, kAEOR, or kAENOT
errAENoSuchObject	-1728	A run-time resolution error, for example: object specifier record asked for the third element, but there are only two
errAENotAEDesc	-1704	Not a valid descriptor record

errAENotAnObjectSpec	-1727	The objSpecifier parameter of AEResolve is not an object specifier record
errAENotAppleEvent	-1707	Event is not an Apple event
errAENotASpecialFunction	-1714	The keyword is not valid for a special function
errAENoUserInteraction	-1713	No user interaction allowed
errAEParamMissed	-1715	Handler cannot understand a parameter the client considers required
errAERecordingIsAlreadyOn	-1732	Attempt to turn recording on when it is already on
errAEReplyNotArrived	-1718	Reply has not yet arrived
errAEReplyNotValid	-1709	AEResetTimer was passed an invalid reply
errAETimeout	-1712	Apple event timed out
errAEUnknownAddressType	-1716	Unknown Apple event address type
errAEUnknownObjectType	-1731	Descriptor type of token returned by AEResolve is not known to server application
errAEUnknownSendMode	-1710	Invalid sending mode was passed
errAEWaitCanceled	-1711	User canceled out of wait loop for reply or receipt
errAEWrongDataType	-1703	Wrong descriptor type
errAEWrongNumberArgs	-1721	The number of operands provided for the kAENot logical operator is not 1
errAttention	-1276	Attention message too long
errBadConverterID	-8979	The 'PDEF' converter doesn't exist
errBadConverterIndex	-8984	When saving a spool file to disk, the value of the fileTypeIndex field had no matching entry in the driver
errBadFontKeyType	-8976	Font found in printer is not Type 1, TrueType, or bitmapped font
errBadSpoolFileVersion	-8990	Bad version number in header of spool file
errBitmapFontMissing	-8986	Unable to build bitmap for font
errCouldNotMakeNumberedFilename	-8989	Could not make a unique filename for the spool file
errDidNotDownloadFont	-8985	A PostScript outline could not be found for a PostScript font, and there is no associated 'sfnt' resource
errDSPQueueSize	-1274	Send or receive queue is too small
errFaceListBad	-8997	Entry could not be found in typeface list
errFontNotFound	-8995	Font query reply didn't match any fonts in list of PostScript names
errFwdReset	-1275	Read terminated by forward reset
errInLineTimeout	-8993	The printer is not responding
errNoPagesSpooled	-8980	Application called PrOpenDoc and PrCloseDoc without calling PrOpenPage and PrClosePage in between
errNoPattern	-8978	The pixel pattern could not be found and could not be built
errNoProcSetRes	-8991	The resource describing needed procedure sets is unavailable for the PostScript prolog
errNotAKey	-8998	Key for desired font number and style could not be found in font table
errNullColorInfo	-8981	The getColor function called with null GetColorInfo handle
errOpenDenied	-1273	Open request denied by recipient
errOpening	-1277	Attempt to open connection failed

errOSABadSelector	-1754	Selector not supported by scripting component
errOSABadStorageType	-1752	Illegal storage type
errOSACantCoerce	-1700	Same as errAEC coercionFail; data could not be coerced to the requested data type
errOSACantOpenComponent	-1762	Generic scripting component error; can't connect to scripting component
errOSAComponentMismatch	-1761	Generic scripting component error; parameters are for two different scripting components instead of the same one
errOSACorruptData	-1702	Same as errAECorruptData
errOSADataFormatObsolete	-1758	Data format is obsolete
errOSADataFormatTooNew	-1759	Data format is too new
errOSAInvalidID	-1751	Invalid script ID
errOSANoSuchDialect	-1757	Invalid dialect code
errOSAScriptError	-1753	Error occurred during compilation or execution
errOSASourceNotAvailable	-1756	Source data not available
errOSASystemError	-1750	General scripting system error
errPSFileName	-8987	PostScript file isn't named
errPSFileNameNull	-8982	The filename pointer for the spool file is null
errPSStateUnderflow	-8977	PostScript stack underflow while restoring graphics state
errRefNum	-1280	Bad connection reference number
errSizeListBad	-8996	The size list contained an entry that could not be reconciled with the typeface list
errSpoolFolderIsAFile	-8983	The spool folder is a file instead of a folder
errState	-1278	Bad connection state for this operation
errUnknownPSLevel	-8994	The PostScript level has an unknown value
excessCollsns	-95	Hardware error; excessive collisions on write
extFSErr	-58	Disk has external file system—file system identifier is nonzero; volume belongs to an external file system
extractErr	-3104	Can't find tuple in buffer
extra_data_passed_was_ignored	-26698	
face_already_set	-25985	
face_override_style_font_must_match_style	-26684	
fBsyErr	-47	File is busy; one or more files are open; directory not empty or working directory control block is open; section doing I/O
featureUnsupported	-2053	Movie Toolbox does not support this feature
fidExists	-1301	File ID already exists
fidNotFoundErr	-1300	File ID not found
fill_already_set	-25984	
firstDskErr	-84	First of the range of low-level disk errors
first_glyph_advance_must_be_absolute	-27622	
fLckdErr	-45	File is locked; publisher writing to an edition

fnfErr	-43	File, directory, or edition container not found; target not found, but volume and parent directory found; for FindFolder: type not found in 'fld#' resource, or disk doesn't have System Folder support or System Folder in volume header, or disk does not have desktop database support for Desktop Folder—in all cases, folder not found; for ResolveAliasFile: target not found, but volume and parent directory found and theSpec parameter contains a valid file system specification record
fnOpnErr	-38	File not open
font_already_set	-25983	
font_cannot_be_changed	-27944	
font_glyph_index_out_of_range		
	-26891	
font_language_not_found	-26843	
font_name_not_found	-26696	
font_not_disposed	-25945	
font_not_found_during_unflattening		
	-26842	
font_not_in_font_list	-27523	
font_scaler_api_version_mismatch		
	-27882	
font_scaler_bitmap_allocation_failed		
	-27893	
font_scaler_fake_linespacing		
	-26848	
font_scaler_fake_metrics	-26849	
font_scaler_fixed_overflow		
	-27883	
font_scaler_getfonttable_failed		
	-27894	
font_scaler_glyph_substitution		
	-26847	
font_scaler_hinting_error		
	-27887	
font_scaler_internal_error		
	-27885	
font_scaler_invalid_matrix		
	-27884	
font_scaler_newblock_failed		
	-27895	
font_scaler_no_kerning_applied		
	-26846	
font_scaler_no_output	-26850	
font_scaler_outline_allocation_failed		
	-27892	
font_scaler_rasterizer_error		
	-27886	
font_scaler_streaming_aborted		
	-27881	
font_table_index_out_of_range		
	-26892	

font_table_not_found	-26697	
font_variations_already_set	-25982	
font_wrong_size	-27527	
font_wrong_type	-27528	
fragAppNotFound	-2822	No application found in 'cfrg' resource
fragArchErr	-2823	Fragment targeted for unacceptable architecture
fragConnectionIDNotFound	-2801	Connection ID is not valid
fragConstErr	-2819	Internal inconsistency discovered
fragContextNotFound	-2800	Context ID is not valid
fragCorruptErr	-2820	Fragment container is corrupted
fragDupRegLibName	-2805	Registered name already in use
fragFormatUnknown	-2806	Fragment container format unknown
fragHadUnresolveds	-2807	Loaded fragment has unacceptable unresolved symbols
fragImportTooNew	-2814	Import library is too new
fragImportTooOld	-2813	Import library is too old
fragInitLoop	-2815	Circularity in required initialization order
fragInitRtnUsageErr	-2816	Boot library has initialization routine
fragInvalidFragmentUsage	-2824	Fragment is used invalidly
fragLibConnErr	-2817	Error connecting to library
fragLibNotFound	-2804	Library name not found in fragment registry
fragMgrInitErr	-2818	Error during Code Fragment Manager initialization
fragNoAddrSpace	-2810	Not enough memory in user's address space for section
fragNoContextIDs	-2811	No more context IDs available
fragNoErr	0	No error
fragNoMem	-2809	Not enough memory for internal bookkeeping
fragObjectInitSeqErr	-2812	Order error during user initialization function
fragSectionNotFound	-2803	Section was not found
fragSymbolNotFound	-2802	Symbol was not found in connection
fragUserInitProcErr	-2821	Initialization procedure did not return noErr
frequency_parameter_out_of_range	-27682	
fsDSIntErr	-127	Internal file system error
fsRnErr	-59	Problem during rename
functionality_unimplemented	-27700	
generalPSErr	-8133	A PostScript error occurred during transmission of data to the printer; this is most often caused by a bug in the application-supplied PostScript code
geometry_unaffected	-25959	
gestaltDupSelectorErr	-5552	Selector already exists
gestaltLocationErr	-5553	Function not in system heap
gestaltUndefSelectorErr	-5551	Undefined selector
gestaltUnknownErr	-5550	Could not obtain the response
gfpErr	-52	Error during GetFPos
glyph_empty	10	There is no glyph to draw
glyph_first_advance_bit_set_not_allowed	-27556	
glyph_index_too_small	-27678	
glyph_not_added_to_font	-27676	
glyph_positions_are_already_set		

	-25981	
glyph_positions_determined_by_advance	-25943	
glyph_run_count_negative	-27559	
glyph_run_count_zero	-27558	
glyph_run_counts_do_not_sum_to_character_count	-27557	
glyph_tangent_vectors_both_zero	-27555	
glyph_tangents_are_already_set	-25980	
glyph_tangents_have_no_effect	-25944	
graphic_type_cannot_be_dashed	-27628	
graphic_type_cannot_be_inset	-27626	
graphic_type_cannot_be_mapped	-27634	
graphic_type_cannot_be_moved	-27633	
graphic_type_cannot_be_reduced	-27627	
graphic_type_cannot_be_reset	-27629	
graphic_type_cannot_be_rotated	-27631	
graphic_type_cannot_be_scaled	-27632	
graphic_type_cannot_be_skewed	-27630	
graphic_type_does_not_contain_points	-27636	
graphic_type_does_not_have_a_structure	-27652	
graphic_type_does_not_have_multiple_contours	-27635	
graphics_client_memory_is_already_allocated	-27645	
graphics_client_memory_too_small	-27646	
graphics_routine_selector_is_obsolete	-27648	
guestNotAllowedErr	-932	Destination port requires authentication
gxFirstFatalError	-27999	
gxFirstFontScalerError	-27900	
gxFirstFontScalerWarning	-26850	
gxFirstImplementationLimitError	-27800	
gxFirstNonFatalError	-27950	
gxFirstParameterError	-27850	
gxFirstParameterOutOfRangeWarning	-26900	

gxFirstResultOutOfRangeWarning	-26950	
gxFirstSystemDebuggingError	-27700	
gxFirstSystemDebuggingWarning	-26700	
gxFirstSystemError	-27999	
gxFirstSystemNotice	-25999	
gxFirstSystemWarning	-26999	
gxLastFatalError	-27951	
gxLastFontScalerError	-27851	
gxLastSystemError	-27000	
gxLastSystemNotice	-25500	
gxLastSystemWarning	-26000	
halftone_already_set	-25979	
hit_test_already_set	-25978	
hmBalloonAborted	-853	Because of constant cursor movement, the help balloon wasn't displayed
hmCloseViewActive	-863	Balloon can't be removed because Close View is in use
hmHelpDisabled	-850	Help balloons are not enabled
hmHelpManagerNotInited	-855	Help menu not set up
hmNoBalloonUp	-862	No balloon showing
hmOperationUnsupported	-861	Invalid value passed in the method parameter
hmSameAsLastBalloon	-854	Menu and item are same as previous menu and item
hmSkippedBalloon	-857	No help message to fill in
hmUnknownHelpType	-859	Help message record contained a bad type
hmWrongVersion	-858	Wrong version of Help Manager resource
hwParamErr	-502	Processor does not support flushing a range
ignorePlatformShape_not_allowed	-27666	
iIOAbort	-27	I/O error
illegal_font_attributes	-27696	
illegal_font_parameter	-27943	
illegal_font_storage_reference	-27697	
illegal_font_storage_type	-27698	
illegal_type_for_shape	-27643	
iMemFullErr	-108	There is not enough room in the heap zone
incompatibleVoice	-245	Specified voice cannot be used with synthesizer
inconsistent_parameters	-27694	
index_is_less_than_one	-27692	
index_is_less_than_zero	-27693	
index_out_of_range	-26895	
index_out_of_range_in_contour	-26899	
indirect_memory_block_too_large	-27587	
indirect_memory_block_too_small	-27588	
ink_already_set	-25977	
ink_cache_parent_mismatch	-27602	

Inside Macintosh X-Ref

Result Codes

ink_cache_wrong_type	-27607	
ink_is_nil	-27846	
ink_not_disposed	-25949	
ink_wrong_type	-27613	
inputOutOfBounds	-190	Offset or count out of bounds
insufficient_coordinate_space_for_new_device	-26682	
internal_error	-27950	
internal_fatal_error	-27998	
internal_font_error	-27949	
internal_layout_error	-27948	
internalQuickTimeError	-2034	Internal error
interruptsMaskedErr	-624	Called with interrupts masked
invalid_bitImage_fileOffset	-27566	
invalid_bitImage_internal_flag	-27563	
invalid_bitImage_owners	-27565	
invalid_bitImage_rowBytes	-27564	
invalid_bitmap_in_device	-27516	
invalidChunkCache	-2040	The chunk cache is corrupted
invalidChunkNum	-2038	There is no chunk with this chunk number
invalid_client_reference	-27687	
invalid_colorProfile_flags	-27510	
invalid_colorProfile_response_count	-27509	
invalid_colorSet_colorSpace	-27513	
invalid_colorSet_count	-27512	
invalid_colorSet_viewDevice_owners	-27514	
invalidComponentID	-3000	No component has this component identifier; speech channel is uninitialized or bad
invalid_contour_count	-27576	
invalidDataRef	-2012	This data reference is invalid
invalidDataRefContainer	-2049	Invalid data reference
invalid_device_bounds	-27517	
invalid_device_number	-27519	
invalid_device_viewGroup	-27518	
invalid_draw_seed	-27579	
invalidDuration	-2014	This duration value is invalid
invalidEditState	-2023	This edit state is invalid
invalid_fillShape_ownerCount	-27590	
invalid_font_platform	-27526	
invalid_font_scaler_context	-27988	
invalid_font_scaler_font_data	-27896	
invalid_font_scaler_input	-27897	

invalid_frame_seed	-27581	
invalid_graphics_heap_start_pointer	-27686	
invalidHandler	-2013	This handler is invalid
invalid_ink_cache_device	-27596	
invalid_ink_cache_port	-27597	
invalid_lookup_platform	-27524	
invalid_lookup_range	-27525	
invalid_mapping	-27663	
invalid_matrix_flag	-27539	
invalidMedia	-2008	This media is corrupted or invalid
invalid_metrics_flags	-27530	
invalid_metrics_range	-27531	
invalidMovie	-2010	This movie is corrupted or invalid
invalid_nongraphic_globals_pointer	-27685	
invalid_picture_count	-27544	
invalid_pixelSize	-27570	
invalid_pointer	-27583	
invalidRect	-2036	Specified rectangle has invalid coordinates
invalidSampleDescIndex	-2039	Sample description index value invalid
invalidSampleDescription	-2041	This sample description is invalid or corrupted
invalidSampleNum	-2037	There is no sample with this sample number
invalidSampleTable	-2011	This sample table is corrupted or invalid
invalid_seed	-27582	
invalid_shape_cache_device	-27598	
invalid_shape_cache_port	-27599	
invalid_style_cache_device	-27594	
invalid_style_cache_port	-27595	
invalid_text_seed	-27580	
invalidTime	-2015	This time value is invalid
invalidTrack	-2009	This track is corrupted or invalid
invalid_transferMode_colorSpace	-27670	
invalid_transform_cache_device	-27592	
invalid_transform_cache_port	-27593	
invalidTranslationPathErr	-3025	howToTranslate is invalid
invalid_vector_count	-27577	
invalid_viewDevice_reference	-27837	
invalid_viewGroup_reference	-27836	
invalid_viewPort_reference	-27835	
inverseFill_face_must_set_clipLayer_flag	-27671	
ioErr	-36	I/O error; data does not match in read-verify mode
iPrAbort	128	Application or user requested cancel

iPrSavPFile	-1	Problem saving print file
join_already_set	-25976	
justification_already_set	-25975	
kDETCouldNotAddMenuItem	-15014	Could not add item to menu
kDETCouldNotFindCustomView	-15017	Could not find custom view
kDETCouldNotFindMenuItem	-15016	Could not find menu item
kDETCouldNotRemoveMenuItem	-15015	Could not remove item from dynamic menu
kDETInfoPageNotOpen	-15012	Information page not open
kDETInvalidCallback	-15019	Invalid callback
kDETInvalidCommandItemNumber	-15007	Command item number out of range
kDETInvalidDSSpec	-15010	Could not resolve DSSpec
kDETInvalidReqFunction	-15018	Invalid callback routine selector
kDETInvalidTarget	-15005	Target selector invalid
kDETInvalidTargetAspectName	-15000	Could not find aspect named in target selector
kDETInvalidTargetDSSpec	-15003	DSSpec in target selector could not be resolved
kDETInvalidTargetFromNonAspect	-15002	Targeted item doesn't have an aspect
kDETInvalidTargetItemNumber	-15001	Item number in target selector out of range
kDETNoSuchView	-15013	No view found with specified property number
kDETPropertyBusy	-15020	Specified property is being edited
kDETRequestedTypeUnavailable	-15009	Item could not be represented in the specified format
kDETTargetNotAnAspect	-15006	Specified target object not an aspect
kDETUnableToAccessProperty	-15011	Property could not be found
kDETUnableToGetCommandItemSpec	-15008	Unable to retrieve information about item (possibly out of memory)
kDETUnknownTargetSelector	-15004	Selector type in target selector invalid
kIPMAlHdrCorrupt	-15098	Message is corrupt; may not be message
kIPMAbortOfNestedMsg	-15100	Canceled nested message
kIPMAccessDenied	-15141	Access denied
kIPMAAttrNotInHdr	-15106	Specified attribute not in message header
kIPMBadContext	-15118	Invalid reference
kIPMBadMailSlotAttrVal	-15149	Invalid mail slot attribute value
kIPMBadQName	-15112	Invalid queue name
kIPMBinBusy	-15110	Internal error
kIPMBinNeedsConversion	-15114	IPM BIN needs conversion
kIPMBlkNotFound	-15107	Specified block nonexistent
kIPMBlockIsNotNestedMsg	-15101	Block is not message (IPMOpenBlockAsMsg)
kIPMCacheFillError	-15102	Internal error
kIPMCantCreateIPMCatEntry	-15090	Internal error
kIPMContextIsClosing	-15119	Reference is closing
kIPMCorruptDataStructures	-15099	Message is corrupt

kIPMCorruptedBin	-15111	IPM BIN is damaged
kIPMEltBusy	-15116	Message or letter opened (on delete operation)
kIPMEltClosedNotDeleted	-15117	Element was closed but not deleted
kIPMEltNotFound	-15122	No such item or message
kIPMEndOfBin	-15113	Internal error
kIPMeoQ	-15120	No more messages (IPMEnumerateQueue)
kIPMInvalidFilter	-15105	Filter is invalid
kIPMInvalidMsgType	-15091	Message type is invalid; only kIPMOSFormatType allowed when creating a letter
kIPMInvalidOffset	-15093	Bad offset for read or write operation
kIPMInvalidProcHint	-15092	Process hint is invalid
kIPMInvalidSender	-15103	Sender is invalid
kIPMLookupAttrTooBig	-15129	Attribute in lookup is too big
kIPMMgrInternalErr	-15115	Internal error
kIPMMsgTypeReserved	-1511	Message creator and/or type specified not allowed
kIPMNestedMsgOpened	-15097	Nested message opened; cannot do operation
kIPMNoAttrsFound	-15146	No attributes found in lookup
kIPMNoRecipientsYet	-15104	Require recipient to send
kIPMNotInABlock	-15096	Specified starting point not within the message
kIPMPortClosed	-15109	Stream closed
kIPMQBusy	-15126	Specified queue busy; cannot delete
kIPMStreamErr	-15108	Error on stream
kIPMUpdateCatFailed	-15094	Internal error
kMailBadEnclLengthErr	-15044	Invalid data length
kMailBadMSAM	-15066	MSAM unusable for unspecified reason
kMailBadSlotInfo	-15060	Invalid slot information
kMailBadState	-15068	Invalid status setting
kMailHdrAttrMissing	-15043	Required attribute not added to message
kMailIgnoredErr	-15053	MSAM ignored high-level event
kMailInvalidOrder	-15040	Content already closed
kMailInvalidPostItVersion	-15046	Message summary is wrong version
kMailInvalidRequest	-15045	Reference number invalid with this request
kMailInvalidSeqNum	-15041	Invalid message sequence number
kMailLengthErr	-15054	Error occurred in sending the event
kMailMalformedContent	-15061	Content data malformed
kMailMSAMSuspended	-15059	MSAM is suspended
kMailNoMSAMErr	-15056	No such MSAM
kMailNoSuchSlot	-15062	No such slot
kMailNotASlotInQ	-15047	Invalid value for a slot's incoming queue
kMailSlotSuspended	-15058	Slot is suspended
kMailTooManyErr	-15055	IPM Manager or MSAM too busy to handle event
kOCEAborted	-1632	The call was aborted
kOCEAbortNotSupportedForThisCall	-1631	Abort not supported
kOCEAccessRightsInsufficient	-1542	Stream needs to be authenticated, or not authorized, or someone other than agent trying to TPFC, or problem in server-to-server authentication
kOCEAgentKeyNotFound	-1553	Intermediary's key not found
kOCEAlreadyExists	-1510	Catalog with same name and kind already exists; duplicate recipient type
kOCEAmbiguousMatches	-1569	Ambiguous matches found in resolving CIDs

kOCEAttributeValueTooBig	-1621	Attribute value is larger than kAttrValueMaxBytes bytes
kOCEAuthenticationTrouble	-1571	Authentication process failed; reply incorrect for the challenge sent
kOCEBadEncryptionMethod	-1559	During the authentication process, the ASDSP implementations could not agree on an encryption method to be used (ASDSP can support multiple stream encryption methods. In Release 1, only RC4 and “no encryption” are supported.)
kOCEBadRecordID	-1617	Record name or record type doesn’t match creation ID
kOCEBadStartingAttribute	-1639	Starting attribute index is not within range
kOCEBadStartingRecord	-1638	Starting record index out of range
kOCEBogusArgs	-1614	Args not formatted correctly on the wire
kOCEBufferTooSmall	-1503	Buffer too small for data requested
kOCEConnectionClosed	-1513	Network connection has closed
kOCECredentialsExpired	-1546	Current time is later than credentials expiration time
kOCECredentialsImmature	-1545	Credentials not yet valid
kOCECredentialsProblem	-1544	Couldn’t decrypt credentials
kOCEDatabaseFull	-1612	The disk is full
kOCEDirectoryCorrupt	-1646	Serious disk fill corruption problem
kOCEDirectoryIdentitySetupDoesNotExist	-1564	Catalog has not been set up
kOCEDirectoryIdentitySetupExists	-1563	Catalog has already been set up
kOCEDirectoryNotFoundErr	-1630	Catalog was not found in the list
kOCEDirListFullErr	-1629	The catalog list is full; try removing an entry
kOCEDisallowedRecipient	-1549	Recipient record ID does not appear in proxy
kOCENodeUnavailable	-1616	Could not find any servers that serve the requested dNode
kOCEDSAMInstallErr	-1628	CSAM could not be installed or doesn’t exist
kOCEDSAMNotInstantiated	-1635	CSAM is not instantiated
kOCEDSAMRecordExists	-1636	CSAM record is already in Setup catalog
kOCEDSAMRecordNotFound	-1634	CSAM record not found
kOCEInitiatorKeyProblem	-1558	No key, or initiator’s key changed
kOCEInternalErr	-1506	Serious internal error
kOCEInvalidRecipient	-1514	Bad recipient
kOCEInvalidRef	-1502	Invalid message reference number
kOCEKeyAlreadyRegistered	-1554	A key already exists
kOCELengthError	-1637	The supplied buffer was too small
kOCELocalAuthenticationFail	-1561	Local identity locked; user hasn’t entered Key Chain password
kOCELocalIdentityDoesNotExist	-1560	Local identity has not been set up
kOCELocalIdentitySetupExists	-1562	Local identity setup exists, use AuthChangeLocalIdentity instead
kOCEMalFormedKey	-1555	Key not derived properly from password
kOCEMiscError	-1643	Miscellaneous error
kOCEMoreAttrValue	-1640	Buffer too small for a single attribute value
kOCEMoreData	-1623	Buffer was too small to hold all available data; more data available

kOCENoASDSPWorkSpace	-1570	No ASDSP workspace passed; you passed NIL for the workspace parameter
kOCENoDupAllowed	-1641	Duplicate record name and type
kOCENoKeyFound	-1550	No key was found
kOCENoMoreIDs	-1566	Identity table is full
kOCENoSuchAttributeType	-1642	Can't find specified attribute type
kOCENoSuchAttributeValue	-1619	Can't find specified attribute value
kOCENoSuchDNode	-1615	Can't find specified dNode
kOCENoSuchIcon	-1644	There is no matching icon from OCGetDirectoryIcon
kOCENoSuchPseudonym	-1620	The specified pseudonym does not exist
kOCENoSuchRecord	-1618	Can't find specified record
kOCENotLocal	-1610	The server does not serve the requested dNode; internal AOCE error
kOCENotLocalIdentity	-1565	You cannot unbind a local identity
kOCEOCESetupRequired	-1633	LocalIdentity Setup is required; local identity is not set up
kOCEOperationDenied	-1568	Local identity operation denied
kOCEOperationNotSupported	-1626	The specified catalog does not support this operation
kOCEPABNotOpen	-1627	The specified personal catalog is not open to make the operation
kOCEParamErr	-50	Invalid parameter
kOCEPrincipalKeyNotFound	-1551	Couldn't decode proxy because principal has no key
kOCEProxyExpired	-1548	Current time is later than proxy expiration time
kOCEProxyImmature	-1547	Proxy not yet valid
kOCEReadAccessDenied	-1540	Identity lacks read access privileges
kOCERecipientKeyNotFound	-1552	The recipient key was not found
kOCERefIsClosing	-1516	IPM Manager is shutting down the personal MSAM, or server MSAM's mail server is shutting down
kOCERefNumBad	-1624	RefNum is not valid
kOCERLIsDontMatch	-1645	RLIs of different records in the record list are not the same
kOCEStreamCreationErr	-1625	Error in creating connection to server; error occurred in creating the stream
kOCETargetDirectoryInaccessible	-1613	Target catalog is not currently available; catalog server not responding
kOCETooBusy	-1611	Server cannot complete call at this time
kOCEToolboxNotOpen	-1500	Collaboration toolbox is shutting down
kOCETypeExists	-1622	The type already exists in the record
kOCEUndesirableKey	-1556	Password too short or resulting key is undesirable
kOCEUnknownID	-1567	Authentication identity is not valid
kOCEUnsupportedCredentialsVersion	-1543	Credentials version not supported
kOCEVersionErr	-1504	Need to sort personal catalog; wrong version of nested message
kOCEWriteAccessDenied	-1541	Identity lacks write access privileges
kOCEWrongIdentityOrKey	-1557	Incorrect key for client
kSDPNoSearchText	-1950	No text is in Find panel text field
kSDPNoSelection	-1952	No selection is in Catalog-Browsing panel
kSDPPersonalDirectoryRepairFailed	-1953	Cannot sort personal catalog

kSDPTooManyLoginAttempts	-1951	User tried more than 3 incorrect passwords
kSIGCertificateQueryDenied	-1971	Can't query certificates with this context
kSIGContextPrepareErr	-1979	Context either corrupted or already prepared with SIGVerifyPrepare, SIGSignPrepare, or SIGDigestPrepare
kSIGConversionErr	-1981	Unable to convert an attribute to Macintosh format
kSIGIndexErr	-1974	Index given is outside the range of allowable values
kSIGInternalsErr	-1977	Bad digest, context, or signature
kSIGInvalidCredentialErr	-1973	Verified OK but credential either pending or expired
kSIGNoDigestErr	-1980	No digest in the signature
kSIGNoSignature	-1983	Standard file signature not found
kSIGOperationIncompatibleErr	-1970	Context in use for different type of operation
kSIGPasswordErr	-1976	Password is incorrect
kSIGSignerErr	-1975	Problem with the signer file or signature
kSIGSignerNotValidErr	-1982	Signer file has either expired or is not yet valid
kSIGToolboxNotPresentErr	-1978	For servers; not returned by the toolbox
kSIGVerifyFailedErr	-1972	Verification failed
kSMPAddressAlreadyInList	-1922	Specified address is in Recipients field
kSMPCannotSendReceivedLetter	-1914	Letter is received; cannot be sent
kSMPCCommandDisabled	-1908	Requested command unavailable
kSMPComponentIsAlreadyTarget	-1920	The selected field is the target
kSMPCopyInProgress	-1901	Enclosure being copied to mailer
kSMPFinderNotRunning	-1907	The Finder is not running
kSMPHasOpenAttachments	-1906	One or more enclosures are open
kSMPIllegalComponent	-1918	Bad field name parameter
kSMPIllegalForDraftLetter	-1915	Operation cannot be completed
kSMPIllegalSendFormats	-1923	Format is not in canSend parameter
kSMPInvalidAddressString	-1924	Address string is invalid
kSMPMailboxNotFound	-1904	Cannot find mailbox
kSMPMailerAlreadyExpandedOrContracted	-1917	Mailer is already in requested state
kSMPMailerAlreadyInWindow	-1911	A mailer was previously allocated
kSMPMailerAlreadyNotTarget	-1919	This mailer is not the target
kSMPMailerCannotExpandOrContract	-1916	Mailer created with canContract false
kSMPMailerNotInitialized	-1902	Mailer has not been initialized
kSMPMailerUneditable	-1912	Mailer cannot be edited
kSMPNoMailerInWindow	-1909	No mailer is in specified window
kSMPNoMatchingBegin	-1913	End function called without begin
kSMPNoNextLetter	-1905	There is no next letter in In Tray
kSMPNoSuchAddress	-1910	Requested address not found
kSMPNotEnoughMemoryForAllRecips	-1900	Too many recipients in mailer
kSMPParamCountErr	-1926	Enclosure count should be 1
kSMPRecordDoesNotContainAddress	-1921	Address is not in this record

kSMPShouldNotAddContent	-1903	You cannot add content to letter
kSMPSubjectTooBig	-1925	Subject string exceeds 127 characters
kSMPTooManyEnclosures	-1928	More than 50 total files and folders
kSMPTooManyPages	-1927	Image is more than 127 pages
LAPProtErr	-94	No protocol handler is attached
lastDskErr	-64	Last of the range of low-level disk errors
layer_glyph_shape_cannot_contain_nil_styles		
	-27617	
layer_style_cannot_contain_a_face		
	-27618	
layout_empty	11	There is no layout to draw
layout_run_length_negative		
	-27554	
layout_run_length_zero	-27553	
layout_run_lengths_do_not_sum_to_text_length		
	-27551	
layout_run_level_negative		
	-27552	
length_is_less_than_zero	-27688	
length_out_of_range	-26893	
localOnlyErr	-905	Network activity is currently disabled
lockShape_called_as_side_effect		
	-25940	
lockTag_called_as_side_effect		
	-25939	
low_on_memory	-25933	
manualFeedTOErr	-8132	A timeout occurred (that is, no communication has occurred with the printer for two minutes); this is usually caused by an extremely long imaging time or a dropped connection
mapping_already_set	-25974	
mapping_is_nil	-27838	
mapping_unaffected	-25958	
map_points_out_of_range	-26940	
mapReadErr	-199	Map inconsistent with operation
map_shape_out_of_range	-26950	
map_transform_out_of_range		
	-26945	
maxSizeToGrowTooSmall	-2027	Maximum size must be larger
mediaTypesDontMatch	-2018	These media don't match
memBCErr	-115	Block check failed
memFragErr	-601	Not enough room to launch application with special requirements
memFullErr	-108	Insufficient memory available; not enough memory to allocate the partition size specified in the 'SIZE' resource
memLockedErr	-117	Block is locked
memPurErr	-112	Attempt to purge a locked block
memROZErr	-99	Operation on a read-only zone
memWZErr	-111	Attempt to operate on a free block
method_parameter_out_of_range		
	-27680	
metrics_maxWidth_probably_bad		

	-27529	
metrics_not_in_metrics_list	-27522	
metrics_point_size_probably_bad	-27536	
metrics_wrong_type	-27537	
mnNotSupported	-1022	Multinode is not supported by the current AppleTalk connection file of type 'adev'
move_shape_out_of_range	-26949	
move_transform_out_of_range	-26944	
movieToolboxUninitialized	-2020	You haven't initialized the Movie Toolbox
multiplePublisherWrn	-460	Already is a publisher
nameTypeErr	-902	Invalid or inappropriate locationKindSelector in location name
nbpConfDiff	-1026	Name confirmed for different socket
nbpDuplicate	-1027	Location name represents a duplicate on this computer
nbpNoConfirm	-1025	Name not confirmed
nbpNotFound	-1028	Name not found
networkErr	-925	An error has occurred in the network
new_shape_contains_invalid_data	-26700	
new_tag_contains_invalid_data	-26699	
nilHandleErr	-109	Handle argument is NIL; NIL master pointer
nil_style_in_glyph_not_allowed	-27665	
nmTypeErr	-299	Invalid qType value (must be ORD(nmType))
noBridgeErr	-93	Could not find router to forward packet
noCodecErr	-8961	Image Compression Manager could not find specified error; Image Compression Manager could not find the specified compressor
noDataArea	-1104	Too many outstanding ATP calls
noDataHandler	-2007	Media has no data handler
noDefaultDataRef	-2051	Could not find a default data reference
noDefaultUserErr	-922	User has not specified owner name in Sharing Setup control panel
no_draw_error	0	No error in drawing
noErr	0	No error
noGlobalsErr	-904	System unable to allocate memory, critical error
no_glyphs_added_to_font	-27677	
noHardwareErr	-200	Required sound hardware not available
noInformErr	-926	PPCStart failed because target application did not have an inform pending
noMacDskErr	-57	Volume lacks Macintosh-format directory
noMaskFoundErr	-1000	Cannot find or create mask for the icon family
noMediaHandler	-2006	Media has no media handler
noMemForPictPlaybackErr	-145	Insufficient memory for drawing the picture
noMoreMultiNodes	-1023	No node address is available on the network
noMoreRealTime	-212	Not enough CPU time available
noMovieFound	-2048	Toolbox cannot find a movie in the movie file
noMPPErr	-3102	The .MPP driver is not installed

nonMatchingEditState	-2024	This edit state is not valid for this movie
no_outline_font_found	-27997	
noOutstandingHLE	-608	No outstanding high-level event
no_owners	-27584	
noPortErr	-903	Client hasn't set 'SIZE' resource to indicate awareness of high-level events; unable to open port; bad port reference number; invalid port name
noPrefAppErr	-3032	No translation preference available
noRelErr	-1101	No release received; timer expired before MSAM responded
noResponseErr	-915	Unable to contact application
noScrapErr	-100	Scrap does not exist (not initialized)
noSendResp	-1103	PAddResponse issued before PSendResponse
noSessionErr	-908	Invalid session reference number
noSuchRsl	1	Resolution requested with the PrGeneral procedure is not supported
noSynthFound	-240	Could not find the specified speech synthesizer
notAFileErr	-1302	Specified file is a directory
notBTree	-410	File is not a dictionary
notEnoughBufferSpace	-207	Insufficient memory available
notEnoughHardwareErr	-201	Insufficient hardware available
notEnoughMemoryErr	-620	Insufficient physical memory
not_enough_memory_for_graphics_client_heap	-27996	
notHeldErr	-621	Specified range of memory is not held
notice_stack_overflow	-26996	
notice_stack_underflow	-26997	
notInitErr	-900	PPC Toolbox has not been initialized yet
notLockedErr	-623	Specified range of memory is not locked
notLoggedInErr	-923	Default user reference number does not yet exist
notOpenErr	-28	AppleTalk is not open; driver not open
noTranslationPathErr	-3030	Application cannot open document
noTransSysInstalledErr	-3027	No translation systems installed
notRegisteredSectionErr	-452	Not registered
notThePublisherWrn	-463	Not the publisher
noTypeErr	-102	Format not available; no data of the requested scrap format type in scrap; unrecognized file type
noUserInteractionAllowed	-610	Background application sends event requiring authentication; cannot interact directly with user
noUserNameErr	-911	User name unknown on destination machine
noUserRecErr	-928	Invalid user reference number
noUserRefErr	-924	Unable to create a new user reference number
nsDrvErr	-56	Specified drive number doesn't match any number in the drive queue
nsStackErr	-149	Insufficient stack
nsvErr	-35	Volume not found
null_font_scaler_context	-27900	
null_font_scaler_input	-27899	
number_of_colors_exceeds_implementation_limit	-27794	
number_of_contours_exceeds_implementation_limit	-27800	
number_of_points_exceeds_implementation_limit		

	-27799	
object_wrong_type	-27616	
openErr	-23	Unable to open device driver; requested read/write permission does not match driver's open permission
opNotImpl	2	Requested <code>PrGeneral</code> opcode not implemented in the current printer driver
opWrErr	-49	File already open with write permission
out_of_memory	-27999	
PAPActive	-4098	The request is already active
PAPBadRefnum	-4097	Bad connection reference number
PAPConnClosed	-4100	The connection is closed
PAPNoCCBs	-4096	There are no free connect control blocks (CCBs) available
PAPNoPrinter	-4101	The printer is not found, is closed, or is not selected
PAPTooBig	-4099	The write request is too big
paramErr	-50	Drive number specified is bad; error in parameter list; invalid parameter (for example, value of handler pointer is <code>NIL</code> or odd); use <code>PBDTGetPath</code> ; process serial number is invalid
parameter_is_nil	-27850	
parameter_out_of_range	-27695	
parameters_have_no_effect	-25999	
path_empty	6	There is no contour to draw
pattern_already_set	-25973	
pattern_empty	23	The pattern shape was specified as an empty type shape
pattern_lattice_out_of_range	-27683	
pen_already_set	-25972	
pen_too_small	19	The pen width is so small that it doesn't enclose any pixels and therefore doesn't draw
permErr	-54	Attempt to open locked file for writing; not a subscriber
pictInfoIDErr	-11001	Invalid picture information ID
pictInfoVerbErr	-11002	Invalid verb combination specified
pictInfoVersionErr	-11000	Version number not 0
picture_cannot_contain_itself	-27621	
pictureDataErr	-11005	Invalid picture data
picture_empty	12	There is no shape in the picture
picture_expected	-27640	
picture_index_out_of_range	-26898	
pixmapTooDeepErr	-148	Pixel map is deeper than 1 bit per pixel
pmBusyErr	-13000	Power ManagerIC stuck busy
pmRecvEndErr	-13005	During receive, Power Manager did not finish handshake
pmRecvStartErr	-13004	During receive, Power Manager did not start handshake
pmReplyTOErr	-13001	Timed out waiting to begin reply handshake
pmSendEndErr	-13003	During send, Power Manager did not finish handshake
pmSendStartErr	-13002	Power ManagerIC did not start handshake

point_does_not_intersect_bitmap	-27675	
point_does_not_intersect_port	-26686	
point_out_of_range	-26890	
polygon_empty	5	There is no contour to draw
port_cache_parent_mismatch	-27600	
port_cache_wrong_type	-27605	
portClosedErr	-916	The port was closed
portInUse	-97	Driver open error code indicating that the port is in use
portNameExistsErr	-910	Another port is already open with this name
portNotCf	-98	Driver open error code indicating that the parameter RAM is not configured for this connection; port is not configured
port_wrong_type	-27610	
posErr	-40	Attempt to position mark before start of file
prInitErr	-88	Validity status is not \$A8
procedure_not_reentrant	-27793	
procNotFound	-600	No eligible process with specified process serial number
profile_response_out_of_range	-26889	
progressProcAborted	-2019	Your progress procedure returned an error
prWrErr	-87	Parameter RAM written did not verify
qErr	-1	Entry is not in specified queue; queue element not found
queueFull	-203	No room in the queue
rcDBAsyncNotSupp	-809	The database extension does not support asynchronous calls
rcDBBadAsynchPB	-810	Invalid parameter block specified
rcDBBadDDev	-808	Couldn't find the specified database extension, or error occurred in opening database extension
rcDBBadSessID	-806	Session ID is invalid
rcDBBadSessNum	-807	Invalid session number
rcDBBadType	-803	Next data item not of requested data type
rcDBBreak	-804	Function timed out
rcDBError	-802	Error executing function
rcDBExec	-805	Query currently executing
rcDBNoHandler	-811	There is no handler for this data type installed for the current application
rcDBNull	-800	The data item was NULL
rcDBPackNotInited	-813	The InitDBPack function has not yet been called
rcDBValue	-801	Data available or successfully retrieved
rcDBWrongVersion	-812	Wrong version number
readErr	-19	Driver does not respond to read requests
recordDataTooBigErr	-20001	Entry data bigger than buffer size
rectangle_zero_height	4	The rectangle doesn't have an area to draw
rectangle_zero_width	3	The rectangle doesn't have an area to draw
rectangles_cannot_be_inserted_into	-27650	
recursive_caches	-27591	

recursive_fillShapes	-27589	
regionTooBigError	-147	Region too big or complex
reqAborted	-1105	
reqFailed	-1096	Request to contact router failed; retry count exceeded
required_font_scaler_table_missing	-27891	
required_font_table_not_present	-27674	
resAttrErr	-198	Attribute inconsistent with operation
resFNotFound	-193	Resource file not found
resNotFound	-192	Resource not found; unable to read resource; the current printer driver does not support PrGeneral—you should clear this error with a call to PrSetError with a parameter value of 0 (otherwise, PrError might still contain this error next time you check it)
resourceInMemory	-188	Resource already in memory
resProblem	-204	Problem loading the resource
rfNumErr	-51	Reference number invalid; reference number specifies nonexistent access path; bad working directory reference number
rgnTooBigErr	-500	Bitmap would convert to a region greater than 64 KB
rmvResFailed	-196	RemoveResource procedure failed
rotate_shape_out_of_range	-26947	
rotate_transform_out_of_range	-26942	
sameFileErr	-1306	Source and destination files are the same
scalar_block_parent_mismatch	-27534	
scalar_block_too_large	-27532	
scalar_block_too_small	-27533	
scalar_block_wrong_type	-27535	
scale_shape_out_of_range	-26948	
scale_transform_out_of_range	-26943	
scArbNBErr	3	Bus busy, arbitration timeout
scBadParmsErr	4	Bad parameter or unrecognized TIB instruction
scBusTOErr	9	Bus timeout during blind transfer
scCommErr	2	Communications error, operation timeout
scCompareErr	6	Comparison error from scComp instruction
scComplPhaseErr	10	SCSI bus was not in status phase on entry to SCSIComplete
scMgrBusyErr	7	SCSI Manager busy
scPhaseErr	5	Phase error on the SCSI bus
scSequenceErr	8	Attempted operation is out of sequence
scsiAutosenseFailed	-7920	Automatic REQUEST SENSE command failed
scsiBDRsent	-7913	A SCSI bus device reset (BDR) message was sent to the target
scsiBusInvalid	-7869	The bus ID is invalid
scsiBusy	-7887	SCSI subsystem is busy
scsiCDBLengthInvalid	-7863	The CDB length supplied is not supported by this SIM; typically this means it was too big
scsiCDBReceived	-7910	The SCSI CDB was received

scsiCommandTimeout	-7925	The timeout value for this parameter block was exceeded and the parameter block was aborted
scsiDataRunError	-7918	Data overrun/underrun error
scsiDataTypeInvalid	-7865	SIM does not support the requested <code>scsiDataType</code>
scsiDeviceConflict	-7883	Attempt to register more than one driver to a device
scsiDeviceNotThere	-7885	SCSI device not installed or available
scsiFunctionNotAvailable	-7871	The requested function is not supported by this SIM
scsiIdentifyMessageRejected	-7924	The target issued a REJECT message in response to the IDENTIFY message; the LUN probably does not exist
scsiIDInvalid	-7866	The initiator ID is invalid
scsiLUNInvalid	-7867	The logical unit number is invalid
scsiMessageRejectReceived	-7923	REJECT message received
scsiNoHBA	-7884	No HBA detected
scsiNoNexus	-7911	Nexus is not established
scsiNonZeroStatus	-7932	The target returned non-zero status upon completion of the request
scsiNoSuchXref	-7882	No driver has been cross-referenced with this device
scsiParityError	-7921	An uncorrectable parity error occurred
scsiPBLengthError	-7872	The parameter block length is too small for this SIM
scsiProvideFail	-7886	Unable to provide the requested service
scsiQLinkInvalid	-7881	The <code>qLink</code> field was not 0
scsiRequestAborted	-7934	Parameter block request aborted by the host
scsiRequestInProgress	1	Parameter block request is in progress
scsiRequestInvalid	-7870	The parameter block request is invalid
scsiSCSIBusReset	-7922	Execution of this parameter block was halted because of a SCSI bus reset
scsiSelectTimeout	-7926	Target selection timeout
scsiSequenceFail	-7916	Target bus phase sequence failure
scsiTerminated	-7912	Parameter block request terminated by the host
scsiTIDInvalid	-7868	The target ID is invalid
scsiTooManyBuses	-7888	SIM registration failed because the XPT registry is full
scsiTransferTypeInvalid	-7864	The <code>scsiTransferType</code> is not supported by this SIM
scsiUnableToAbort	-7933	Unable to abort parameter block request
scsiUnableToTerminate	-7927	Unable to terminate I/O parameter block request
scsiUnexpectedBusFree	-7917	Unexpected bus free phase
scsiWrongDirection	-7915	Data phase was in an unexpected direction
scTypeNotFoundErr	-8971	Component does not have the information you want
sessClosedErr	-917	The <code>kAEDontReconnect</code> flag in the <code>sendMode</code> parameter was set, and the server quit and then restarted; the session has closed
sessTableErr	-907	PPC Toolbox is unable to create a session
shape__may_not_be_a_picture	-27637	
shape_access_not_allowed	-27657	
shape_already_broken	-25954	
shape_already_in_primitive_form	-25956	
shape_already_in_simple_form	-25955	
shape_already_joined	-25953	
shape_cache_parent_mismatch		

	-27604	
shape_cache_wrong_type	-27609	
shape_cannot_be_inverted	-27625	
shape_contours_cancel	18	The shapes contours overlap and cancel each other out
shape_direct_attribute_not_set	-26687	
shape_does_not_have_length	-27623	
shape_does_not_contain_a_bitmap	-27642	
shape_does_not_contain_text	-27641	
shape_does_not_have_area	-27624	
shape_emptyType	1	An empty type doesn't have an area to draw
shape_inverse_fullType	2	An inverse full type doesn't have an area to draw
shape_is_nil	-27849	
shape_may_not_be_a_bitmap	-27638	
shape_no_enclosed_area	14	There is no enclosed area to draw
shape_no_enclosed_pixels	15	There is an enclosed area, but it is so small that it does not cross any pixel centers
shape_no_fill	13	The shape fill is set to <code>gxNoFill</code> , which will not draw
shape_not_disposed	-25951	
shape_not_locked	-25937	
shape_passed_has_no_bounds	-26681	
shape_primitive_empty	25	The original shape enclosed an area—there is no stylized shape to draw; an example is a pattern shape that contains overlapping patterns that cancel
shape_primitive_very_small	26	There is a shape to draw, but it is extremely small (on the order of the size of a pixel); an example is a scaled transform that shrinks the shape
shape_very_large	17	Part of the shape may be drawn outside the bounds of the coordinate system ($\pm 32,768$)
shape_very_small	16	There is a shape to draw, but it is extremely small (on the order of the size of a pixel)
shape_wrong_type	-27615	
shapeFill_not_allowed	-27672	
shapes_unlocked_as_side_effect	-25938	
siBadDeviceName	-228	Invalid device name
siBadRefNum	-229	Invalid reference number
siBadSoundInDevice	-221	Invalid sound input device
siDeviceBusyErr	-227	Sound input device is busy
siHardDriveTooSlow	-224	Hard drive too slow to record
siInputDeviceErr	-230	Input device hardware failure
siInvalidCompression	-223	Invalid compression type
siInvalidSampleRate	-225	Invalid sample rate
siInvalidSampleSize	-226	Invalid sample size
siNoBufferSpecified	-222	No buffer specified
siNoSoundInHardware	-220	No sound input hardware available

siUnknownInfoType	-231	Feature not implemented on synthesizer; unknown type of information
siUnknownQuality	-232	Unknown quality
size_of_bitmap_exceeds_implementation_limit	-27795	
size_of_path_exceeds_implementation_limit	-27797	
size_of_polygon_exceeds_implementation_limit	-27798	
size_of_text_exceeds_implementation_limit	-27796	
skew_shape_out_of_range	-26946	
skew_transform_out_of_range	-26941	
slotNumErr	-360	Invalid slot number
smBadRefId	-330	Reference ID was not found in the given list
smBadsList	-331	The IDs are not in ascending order
smBadsPtrErr	-346	Bad spsPointer value
smBLFieldBad	-309	A valid fhByteLanes field was not found
smByteLanesErr	-347	Bad spByteLanes value
smCkStatusErr	-341	Status of slot is bad
smCodeRevErr	-333	The revision of the code to be executed by sExec was wrong
smCPUErr	-334	The CPU field of the code to be executed by sExec was wrong
smCRCFail	-301	CRC check failed
smDisposePErr	-312	An error occurred during execution of DisposePtr
smEmptySlot	-300	No card in this slot
smFormatErr	-302	The format of the declaration ROM is wrong
smGetDrvrNamErr	-342	An error occurred during execution of _sGetDrvrName
smInitStatVErr	-316	The InitStatusV field was negative after PrimaryInit
smNilsBlockErr	-336	The physical block size of an sBlock was zero
smNoBoardId	-315	There is no board ID
smNoBoardsRsrc	-313	There is no board sResource
smNoMoresRsrcs	-344	Requested sResource not found
smRecNotFnd	-351	Record not found in the slot resource table
smReservedErr	-332	A reserved field was not zero
smSelOOBErr	-338	Selector out of bounds or function not implemented
smSlotOOBErr	-337	The given slot was out of bounds or does not exist
smsPointerNil	-335	The spsPointer value is NIL: no list is specified
smUnExBusErr	-308	A bus error occurred
space_may_not_be_indexed	-27679	
spoolProcedure_is_nil	-27841	
staleEditState	-2025	Movie or track has been disposed
start_cap_empty	22	The start cap shape was specified as an empty type shape
statusErr	-18	Driver does not respond to this status request
style_already_set	-25971	
style_cache_parent_mismatch	-27603	
style_cache_wrong_type	-27608	

style_is_nil	-27848	
style_not_disposed	-25950	
style_run_array_does_not_match_number_of_characters	-27651	
style_wrong_type	-27614	
synthNotReady	-242	Speech synthesizer is still busy speaking
synthOpenFailed	-241	Could not open another speech synthesizer channel
tag_access_restricted	-27654	
tag_already_set	-25970	
tag_is_nil	-27840	
tag_not_locked	-25936	
tags_in_shape_ignored	-25957	
tags_of_type_flst_removed	-26680	
text_attributes_already_set	-25969	
text_bounds_cache_wrong_size	-27562	
text_empty	9	There is no character to draw
text_index_cache_wrong_size	-27560	
text_metrics_cache_wrong_size	-27561	
text_size_already_set	-25968	
text_size_too_small	20	The text size is so small that it doesn't enclose any pixels and therefore doesn't draw
textFace_Empty	24	Each layer of the text face has a shape fill equal to gxNoFill
timeNotInMedia	-2032	This time value is outside of this media
timeNotInTrack	-2031	This time value is outside of this track
tinting_parameter_out_of_range	-27681	
tmfoErr	-42	Too many files open
tmwdoErr	-121	Too many working directories open
toggleBadChar	4	Invalid character
toggleBadDelta	3	Invalid delta value
toggleBadField	2	Invalid field number
toggleBadNum	6	Tried to use character as number
toggleErr3	7	Reserved
toggleErr4	8	Reserved
toggleErr5	9	Reserved
toggleOK	1	No error
toggleOutOfRange	7	Out of range (synonym for toggleErr3)
toggleUndefined	0	Undefined error
toggleUnknown	5	Unknown error
tooManyReqs	-1097	Too many concurrent requests; wait a few minutes, then try the request again
tooManySks	-1098	Too many responding sockets
trackIDNotFound	-2029	Cannot locate a track with this ID value
trackNotInMovie	-2030	This track is not in this movie
transfer_already_set	-25967	
transfer_equals_noMode	27	The transfer mode gxNoMode suppresses drawing
transfer_matrix_ignores_device		

	29	The transfer mode's mapping scales all values greater than 1 or less than 0 and the overComponent flag is not set
transfer_matrix_ignores_source		
	28	The transfer mode's mapping scales all values greater than 1 or less than 0 and the overComponent flag is not set
transfer_mode_ineffective		
	31	The transfer mode has no effect on the device—an example is a blend with an operand of 0
transfer_source_reject	30	The color is not within the source minimum and the source maximum
transferMode_is_nil	-27845	
transform_already_set	-25965	
transform_cache_parent_mismatch	-27601	
transform_cache_wrong_type	-27606	
transform_clip_empty	42	The transform clip is an empty type shape
transform_clip_missing	-27538	
transform_clip_no_intersection	41	The clip shape does not intersect any view port
transform_is_nil	-27847	
transform_map_too_large	35	The transform has moved all or part of the shape outside the bounds of the coordinate system
transform_move_too_large	36	The transform has moved all or part of the shape outside the bounds of the coordinate system
transform_no_viewPorts	43	The number of entries in the view port list is zero
transform_not_disposed	-25948	
transform_perspective_too_large	39	The transform has moved all or part of the shape outside the bounds of the coordinate system
transform_references_disposed_viewPort	-25931	
transform_rotate_too_large	38	The transform has moved all or part of the shape outside the bounds of the coordinate system
transform_scale_too_large	37	The transform has moved all or part of the shape outside the bounds of the coordinate system
transform_scale_too_small	34	The transform has reduced the shape to less than 1/72 inch—you may see a few pixels drawn, depending on the resolution of your view port
transform_skew_too_large	40	The transform has moved all or part of the shape outside the bounds of the coordinate system
transform_viewPorts_already_set	-25942	
transform_wrong_type	-27612	
translator_already_installed_on_this_grafport	-25966	
translator_not_installed_on_this_grafport	-26679	

tryAddNodeAgainErr	-1021	The .MPP driver was not able to add node; try again
tsmAlreadyRegisteredErr	-2503	The caller is already TSM-initialized
tsmCantOpenComponentErr	-2509	Can't open the component
tsmComponentAlreadyOpenErr	-2515	Text service component already open for document
tsmComponentNoErr	0	Component result: no error
tsmDocNotActiveErr	-2507	Document is not active
tsmDocumentOpenErr	-2511	There are open documents
tsmInputMethodIsOldErr	-2516	The default input method is old-style
tsmInputMethodNotFoundErr	-2501	Specified input method cannot be found
tsmInvalidDocIDErr	-2505	Invalid TSM document ID
tsmNeverRegisteredErr	-2504	The caller is not TSM-aware
tsmNoOpenTSErr	-2508	There is no open text service component
tsmNotAnAppErr	-2502	The caller was not an application
tsmScriptHasNoIMErr	-2517	Script has no (or old) input method
tsmTextServiceNotFoundErr	-2510	No text service component found
tsmTSHasNoMenuErr	-2513	The text service component has no menu
tsmTSMDocBusyErr	-2506	Document is still active
tsmTSNotOpenErr	-2514	Text service component is not open
tsmUnknownErr	-2519	Any other error
tsmUnsupportedTypeErr	-2518	Unsupported interface type
tsmUnsupScriptLanguageErr	-2500	Specified script and language are not supported
tsmUseInputWindowErr	-2512	An input window is being used
type_already_set	-25964	
type_is_nil	-27839	
unable_to_bounds_on_multiple_devices	-26844	
unable_to_draw_open_contour_that_starts_or_ends_off_the_curve	-26694	
unable_to_traverse_open_contour_that_starts_or_ends_off_the_curve	-26695	
unexpected_nil_pointer	-27586	
unflattening_interrupted_by_client	-27945	
unimplMsg	-248	Unimplemented message
union_of_area_and_and_length_returns_area_only	-26683	
unitEmptyErr	-22	Driver reference number specifies a nil handle in unit table
unknown_font_scaler_error	-27880	
unknown_font_table_format	-27673	
unknown_graphics_heap	-27649	
unknownInsertModeErr	-20000	No such insertion mode
unrecognized_stream_version	-26841	
unsupported_font_scaler_font_format	-27888	
unsupported_font_scaler_outline_format		

	-27890	
unsupported_font_scaler_stream_format	-27889	
userCanceledErr	-128	User canceled an operation (e.g., translation, query); user clicked Cancel in dialog box; user decided not to conduct a session
userDataItemNotFound	-2026	Cannot locate this user data item
userRejectErr	-912	Destination rejected the session request
usrCanceledErr	-128	The user canceled the operation
validation_level_already_set		
	-25963	
validInstancesExist	-3001	This component has open connections
very_low_on_memory	-25932	
viewDevice_access_restricted		
	-27653	
viewDevice_already_in_viewGroup		
	-25960	
viewDevice_clip_no_intersection	55	The view device clip does not intersect the bounds described by the view device bitmap shape
viewDevice_map_too_large	57	The view device mapping has moved the shape outside the bounds of the coordinate system
viewDevice_move_too_large		
	58	The view device mapping has moved the shape outside the bounds of the coordinate system
viewDevice_perspective_too_large		
	61	The view device mapping has moved the shape outside the bounds of the coordinate system
viewDevice_rotate_too_large		
	60	The view device mapping has moved the shape outside the bounds of the coordinate system
viewDevice_scale_too_large		
	59	The view device mapping has moved the shape outside the bounds of the coordinate system
viewDevice_scale_too_small		
	56	The mapping to global space has been completed; the object is less than 1/72 inch; you may see a few pixels drawn, depending on the resolution of your draw view port
viewDevice_skew_too_large		
	62	The view device mapping has moved the shape outside the bounds of the coordinate system
viewPort_cannot_contain_itself		
	-27620	
viewPort_clip_empty	45	The view port clip is an empty type shape
viewPort_clip_no_intersection		
	46	The view port clip does not intersect the view device
viewPort_disposed	44	The view port that was to be drawn to has already been disposed of; there is no view port to draw to
viewPort_is_a_window	-27644	
viewPort_map_too_large	48	The view port mapping has moved all or part of the shape outside the bounds of the coordinate system

viewPort_move_too_large	49	The view port mapping has moved all or part of the shape outside the bounds of the coordinate system
viewPort_perspective_too_large	52	The view port mapping has moved all or part of the shape outside the bounds of the coordinate system
viewPort_rotate_too_large	51	The view port mapping has moved all or part of the shape outside the bounds of the coordinate system
viewPort_scale_too_large	50	The view port mapping has moved all or part of the shape outside the bounds of the coordinate system
viewPort_scale_too_small	47	The map to global space has been completed; the object is less than 1/72 inch; you may see a few pixels drawn, depending on the resolution of your view port.
viewPort_skew_too_large	53	The view port mapping has moved all or part of the shape outside the bounds of the coordinate system
viewPort_viewGroup_offscreen	54	The shape is drawn to an off-screen view device (this may be normal); this error is returned to alert you in the event that the drawing result was unexpected
viewPorts_already_in_viewGroup	-25961	
viewPorts_already_set	-25962	
vLckdErr	-46	Volume is locked through software
voiceNotFound	-244	Voice resource not found
volGoneErr	-124	Server volume has been disconnected
volOfflinErr	-53	Volume is offline
volOnLinErr	-55	Volume is already online
vTypErr	-2	Invalid qType value (must be ORD(dtQType)); invalid qType value (must be ORD(vType))
warning_stack_overflow	-26998	
warning_stack_underflow	-26999	
wFileNotFound	-2021	Cannot locate this file
wPrErr	-44	Disk is write-protected; volume is locked through hardware
wrgVolTypErr	-123	Not an HFS volume; volume does not support Desktop Manager
writErr	-20	Driver does not respond to write requests
writingPastEnd	-189	Writing past end of file
wrPermErr	-61	Read/write permission doesn't allow writing; not a publisher
zoomRangeErr	-8160	The print image enlarged by the user with the Page Setup dialog box overflows the available page resolution

Table 2 Result codes (in numerical order)

-27999	gxFirstFatalError
-27999	gxFirstSystemError
-27999	out_of_memory
-27998	internal_fatal_error
-27997	no_outline_font_found
-27996	not_enough_memory_for_graphics_client_heap
-27995	could_not_create_backing_store
-27988	invalid_font_scaler_context
-27951	gxLastFatalError
-27950	gxFirstNonFatalError
-27950	internal_error
-27949	internal_font_error
-27948	internal_layout_error
-27946	could_not_dispose_backing_store
-27945	unflattening_interrupted_by_client
-27944	font_cannot_be_changed
-27943	illegal_font_parameter
-27900	gxFirstFontScalerError
-27900	null_font_scaler_context
-27899	null_font_scaler_input
-27897	invalid_font_scaler_input
-27896	invalid_font_scaler_font_data
-27895	font_scaler_newblock_failed
-27894	font_scaler_getfonttable_failed
-27893	font_scaler_bitmap_allocation_failed
-27892	font_scaler_outline_allocation_failed
-27891	required_font_scaler_table_missing
-27890	unsupported_font_scaler_outline_format
-27889	unsupported_font_scaler_stream_format
-27888	unsupported_font_scaler_font_format
-27887	font_scaler_hinting_error
-27886	font_scaler_rasterizer_error
-27885	font_scaler_internal_error
-27884	font_scaler_invalid_matrix
-27883	font_scaler_fixed_overflow
-27882	font_scaler_api_version_mismatch
-27881	font_scaler_streaming_aborted
-27880	unknown_font_scaler_error
-27851	gxLastFontScalerError
-27850	gxFirstParameterError
-27850	parameter_is_nil
-27849	shape_is_nil
-27848	style_is_nil
-27847	transform_is_nil
-27846	ink_is_nil
-27845	transferMode_is_nil
-27844	color_is_nil
-27843	colorProfile_is_nil
-27842	colorSet_is_nil
-27841	spoolProcedure_is_nil
-27840	tag_is_nil

-27839	type_is_nil
-27838	mapping_is_nil
-27837	invalid_viewDevice_reference
-27836	invalid_viewGroup_reference
-27835	invalid_viewPort_reference
-27800	gxFirstImplementationLimitError
-27800	number_of_contours_exceeds_implementation_limit
-27799	number_of_points_exceeds_implementation_limit
-27798	size_of_polygon_exceeds_implementation_limit
-27797	size_of_path_exceeds_implementation_limit
-27796	size_of_text_exceeds_implementation_limit
-27795	size_of_bitmap_exceeds_implementation_limit
-27794	number_of_colors_exceeds_implementation_limit
-27793	procedure_not_reentrant
-27700	gxFirstSystemDebuggingError
-27700	functionality_unimplemented
-27699	clip_to_frame_shape_unimplemented
-27698	illegal_font_storage_type
-27697	illegal_font_storage_reference
-27696	illegal_font_attributes
-27695	parameter_out_of_range
-27694	inconsistent_parameters
-27693	index_is_less_than_zero
-27692	index_is_less_than_one
-27691	count_is_less_than_zero
-27690	count_is_less_than_one
-27689	contour_is_less_than_zero
-27688	length_is_less_than_zero
-27687	invalid_client_reference
-27686	invalid_graphics_heap_start_pointer
-27685	invalid_nongraphic_globals_pointer
-27684	colorSpace_out_of_range
-27683	pattern_lattice_out_of_range
-27682	frequency_parameter_out_of_range
-27681	tinting_parameter_out_of_range
-27680	method_parameter_out_of_range
-27679	space_may_not_be_indexed
-27678	glyph_index_too_small
-27677	no_glyphs_added_to_font
-27676	glyph_not_added_to_font
-27675	point_does_not_intersect_bitmap
-27674	required_font_table_not_present
-27673	unknown_font_table_format
-27672	shapeFill_not_allowed
-27671	inverseFill_face_must_set_clipLayer_flag
-27670	invalid_transferMode_colorSpace
-27669	colorProfile_must_be_nil
-27668	bitmap_pixel_size_must_be_1
-27667	empty_shape_not_allowed
-27666	ignorePlatformShape_not_allowed
-27665	nil_style_in_glyph_not_allowed
-27664	complex_glyph_style_not_allowed
-27663	invalid_mapping

-27662 cannot_set_item_shapes_to_nil
-27661 cannot_use_original_item_shapes_when_growing_picture
-27660 cannot_add_unspecified_new_glyphs
-27659 cannot_dispose_locked_tag
-27658 cannot_dispose_locked_shape
-27657 shape_access_not_allowed
-27656 colorSet_access_restricted
-27655 colorProfile_access_restricted
-27654 tag_access_restricted
-27653 viewDevice_access_restricted
-27652 graphic_type_does_not_have_a_structure
-27651 style_run_array_does_not_match_number_of_characters
-27650 rectangles_cannot_be_inserted_into
-27649 unknown_graphics_heap
-27648 graphics_routine_selector_is_obsolete
-27647 cannot_set_graphics_client_memory_without_setting_size
-27646 graphics_client_memory_too_small
-27645 graphics_client_memory_is_already_allocated
-27644 viewPort_is_a_window
-27643 illegal_type_for_shape
-27642 shape_does_not_contain_a_bitmap
-27641 shape_does_not_contain_text
-27640 picture_expected
-27639 bitmap_is_not_resizable
-27638 shape_may_not_be_a_bitmap
-27637 shape_may_not_be_a_picture
-27636 graphic_type_does_not_contain_points
-27635 graphic_type_does_not_have_multiple_contours
-27634 graphic_type_cannot_be_mapped
-27633 graphic_type_cannot_be_moved
-27632 graphic_type_cannot_be_scaled
-27631 graphic_type_cannot_be_rotated
-27630 graphic_type_cannot_be_skewed
-27629 graphic_type_cannot_be_reset
-27628 graphic_type_cannot_be_dashed
-27627 graphic_type_cannot_be_reduced
-27626 graphic_type_cannot_be_inset
-27625 shape_cannot_be_inverted
-27624 shape_does_not_have_area
-27623 shape_does_not_have_length
-27622 first_glyph_advance_must_be_absolute
-27621 picture_cannot_contain_itself
-27620 viewPort_cannot_contain_itself
-27619 cannot_set_unique_items_attribute_when_picture_contains_items
-27618 layer_style_cannot_contain_a_face
-27617 layer_glyph_shape_cannot_contain_nil_styles
-27616 object_wrong_type
-27615 shape_wrong_type
-27614 style_wrong_type
-27613 ink_wrong_type
-27612 transform_wrong_type
-27611 device_wrong_type
-27610 port_wrong_type

-27609 shape_cache_wrong_type
 -27608 style_cache_wrong_type
 -27607 ink_cache_wrong_type
 -27606 transform_cache_wrong_type
 -27605 port_cache_wrong_type
 -27604 shape_cache_parent_mismatch
 -27603 style_cache_parent_mismatch
 -27602 ink_cache_parent_mismatch
 -27601 transform_cache_parent_mismatch
 -27600 port_cache_parent_mismatch
 -27599 invalid_shape_cache_port
 -27598 invalid_shape_cache_device
 -27597 invalid_ink_cache_port
 -27596 invalid_ink_cache_device
 -27595 invalid_style_cache_port
 -27594 invalid_style_cache_device
 -27593 invalid_transform_cache_port
 -27592 invalid_transform_cache_device
 -27591 recursive_caches
 -27590 invalid_fillShape_ownerCount
 -27589 recursive_fillShapes
 -27588 indirect_memory_block_too_small
 -27587 indirect_memory_block_too_large
 -27586 unexpected_nil_pointer
 -27585 bad_address
 -27584 no_owners
 -27583 invalid_pointer
 -27582 invalid_seed
 -27581 invalid_frame_seed
 -27580 invalid_text_seed
 -27579 invalid_draw_seed
 -27578 bad_printer_flags
 -27577 invalid_vector_count
 -27576 invalid_contour_count
 -27575 bitmap_ptr_too_small
 -27574 bitmap_ptr_not_aligned
 -27573 bitmap_rowBytes_negative
 -27572 bitmap_width_negative
 -27571 bitmap_height_negative
 -27570 invalid_pixelSize
 -27569 bitmap_rowBytes_too_small
 -27568 bitmap_rowBytes_not_aligned
 -27567 bitmap_rowBytes_must_be_specified_for_user_image_buffer
 -27566 invalid_bitImage_fileOffset
 -27565 invalid_bitImage_owners
 -27564 invalid_bitImage_rowBytes
 -27563 invalid_bitImage_internal_flag
 -27562 text_bounds_cache_wrong_size
 -27561 text_metrics_cache_wrong_size
 -27560 text_index_cache_wrong_size
 -27559 glyph_run_count_negative
 -27558 glyph_run_count_zero
 -27557 glyph_run_counts_do_not_sum_to_character_count

-27556 glyph_first_advance_bit_set_not_allowed
-27555 glyph_tangent_vectors_both_zero
-27554 layout_run_length_negative
-27553 layout_run_length_zero
-27552 layout_run_level_negative
-27551 layout_run_lengths_do_not_sum_to_text_length
-27550 bad_shape_in_picture
-27549 bad_style_in_picture
-27548 bad_ink_in_picture
-27547 bad_transform_in_picture
-27546 bad_shape_cache_in_picture
-27545 bad_seed_in_picture
-27544 invalid_picture_count
-27543 bad_textLayer_count
-27542 bad_fillType_in_textFace
-27541 bad_style_in_textFace
-27540 bad_transform_in_textFace
-27539 invalid_matrix_flag
-27538 transform_clip_missing
-27537 metrics_wrong_type
-27536 metrics_point_size_probably_bad
-27535 scalar_block_wrong_type
-27534 scalar_block_parent_mismatch
-27533 scalar_block_too_small
-27532 scalar_block_too_large
-27531 invalid_metrics_range
-27530 invalid_metrics_flags
-27529 metrics_maxWidth_probably_bad
-27528 font_wrong_type
-27527 font_wrong_size
-27526 invalid_font_platform
-27525 invalid_lookup_range
-27524 invalid_lookup_platform
-27523 font_not_in_font_list
-27522 metrics_not_in_metrics_list
-27521 bad_device_private_flags
-27520 bad_device_attributes
-27519 invalid_device_number
-27518 invalid_device_viewGroup
-27517 invalid_device_bounds
-27516 invalid_bitmap_in_device
-27515 colorSet_wrong_type
-27514 invalid_colorSet_viewDevice_owners
-27513 invalid_colorSet_colorSpace
-27512 invalid_colorSet_count
-27511 colorProfile_wrong_type
-27510 invalid_colorProfile_flags
-27509 invalid_colorProfile_response_count
-27508 backing_free_parent_mismatch
-27507 backing_store_parent_mismatch
-27000 gxLastSystemError
-26999 gxFirstSystemWarning
-26999 warning_stack_underflow

-26998 warning_stack_overflow
 -26997 notice_stack_underflow
 -26996 notice_stack_overflow
 -26995 about_to_grow_heap
 -26994 about_to_unload_objects
 -26950 gxFirstResultOutOfRangeWarning
 -26950 map_shape_out_of_range
 -26949 move_shape_out_of_range
 -26948 scale_shape_out_of_range
 -26947 rotate_shape_out_of_range
 -26946 skew_shape_out_of_range
 -26945 map_transform_out_of_range
 -26944 move_transform_out_of_range
 -26943 scale_transform_out_of_range
 -26942 rotate_transform_out_of_range
 -26941 skew_transform_out_of_range
 -26940 map_points_out_of_range
 -26900 contour_out_of_range
 -26900 gxFirstParameterOutOfRangeWarning
 -26899 index_out_of_range_in_contour
 -26898 picture_index_out_of_range
 -26897 color_index_requested_not_found
 -26896 colorSet_index_out_of_range
 -26895 index_out_of_range
 -26894 count_out_of_range
 -26893 length_out_of_range
 -26892 font_table_index_out_of_range
 -26891 font_glyph_index_out_of_range
 -26890 point_out_of_range
 -26889 profile_response_out_of_range
 -26850 font_scaler_no_output
 -26850 gxFirstFontScalerWarning
 -26849 font_scaler_fake_metrics
 -26848 font_scaler_fake_linespacing
 -26847 font_scaler_glyph_substitution
 -26846 font_scaler_no_kerning_applied
 -26845 character_substitution_took_place
 -26844 unable_to_bounds_on_multiple_devices
 -26843 font_language_not_found
 -26842 font_not_found_during_unflattening
 -26841 unrecognized_stream_version
 -26840 bad_data_in_stream
 -26700 gxFirstSystemDebuggingWarning
 -26700 new_shape_contains_invalid_data
 -26699 new_tag_contains_invalid_data
 -26698 extra_data_passed_was_ignored
 -26697 font_table_not_found
 -26696 font_name_not_found
 -26695 unable_to_traverse_open_contour_that_starts_or_ends_off_the_curve
 -26694 unable_to_draw_open_contour_that_starts_or_ends_off_the_curve
 -26693 cannot_dispose_default_shape
 -26692 cannot_dispose_default_style
 -26691 cannot_dispose_default_ink

-26690 cannot_dispose_default_transform
 -26689 cannot_dispose_default_colorProfile
 -26688 cannot_dispose_default_colorSet
 -26687 shape_direct_attribute_not_set
 -26686 point_does_not_intersect_port
 -26685 cannot_dispose_non_font
 -26684 face_override_style_font_must_match_style
 -26683 union_of_area_and_and_length_returns_area_only
 -26682 insufficient_coordinate_space_for_new_device
 -26681 shape_passed_has_no_bounds
 -26680 tags_of_type_flst_removed
 -26679 translator_not_installed_on_this_grafport
 -26000 gxLastSystemWarning
 -25999 gxFirstSystemNotice
 -25999 parameters_have_no_effect
 -25998 attributes_already_set
 -25997 caps_already_set
 -25996 clip_already_set
 -25995 color_already_set
 -25994 curve_error_already_set
 -25993 dash_already_set
 -25992 default_colorProfile_already_set
 -25991 default_ink_already_set
 -25990 default_transform_already_set
 -25989 default_shape_already_set
 -25988 default_style_already_set
 -25987 dither_already_set
 -25986 encoding_already_set
 -25985 face_already_set
 -25984 fill_already_set
 -25983 font_already_set
 -25982 font_variations_already_set
 -25981 glyph_positions_are_already_set
 -25980 glyph_tangents_are_already_set
 -25979 halftone_already_set
 -25978 hit_test_already_set
 -25977 ink_already_set
 -25976 join_already_set
 -25975 justification_already_set
 -25974 mapping_already_set
 -25973 pattern_already_set
 -25972 pen_already_set
 -25971 style_already_set
 -25970 tag_already_set
 -25969 text_attributes_already_set
 -25968 text_size_already_set
 -25967 transfer_already_set
 -25966 translator_already_installed_on_this_grafport
 -25965 transform_already_set
 -25964 type_already_set
 -25963 validation_level_already_set
 -25962 viewPorts_already_set
 -25961 viewPorts_already_in_viewGroup

-25960	viewDevice_already_in_viewGroup	
-25959	geometry_unaffected	
-25958	mapping_unaffected	
-25957	tags_in_shape_ignored	
-25956	shape_already_in_primitive_form	
-25955	shape_already_in_simple_form	
-25954	shape_already_broken	
-25953	shape_already_joined	
-25952	cache_already_cleared	
-25951	shape_not_disposed	
-25950	style_not_disposed	
-25949	ink_not_disposed	
-25948	transform_not_disposed	
-25947	colorSet_not_disposed	
-25946	colorProfile_not_disposed	
-25945	font_not_disposed	
-25944	glyph_tangents_have_no_effect	
-25943	glyph_positions_determined_by_advance	
-25942	transform_viewPorts_already_set	
-25941	directShape_attribute_set_as_side_effect	
-25940	lockShape_called_as_side_effect	
-25939	lockTag_called_as_side_effect	
-25938	shapes_unlocked_as_side_effect	
-25937	shape_not_locked	
-25936	tag_not_locked	
-25935	disposed_dead_caches	
-25934	disposed_live_caches	
-25933	low_on_memory	
-25932	very_low_on_memory	
-25931	transform_references_disposed_viewPort	
-25500	gxLastSystemNotice	
-20001	recordDataTooBigErr	Entry data bigger than buffer size
-20000	unknownInsertModeErr	No such insertion mode
-15149	kIPMBadMailSlotAttrVal	Invalid mail slot attribute value
-15146	kIPMNoAttrsFound	No attributes found in lookup
-15141	kIPMAccessDenied	Access denied
-15129	kIPMLookupAttrTooBig	Attribute in lookup is too big
-15126	kIPMQBusy	Specified queue busy; cannot delete
-15122	kIPMEltNotFound	No such item or message
-15120	kIPMeoQ	No more messages (IPMEnumerateQueue)
-15119	kIPMContextIsClosing	Reference is closing
-15118	kIPMBadContext	Invalid reference
-15117	kIPMEltClosedNotDeleted	Element was closed but not deleted
-15116	kIPMEltBusy	Message or letter opened (on delete operation)
-15115	kIPMMgrInternalErr	Internal error
-15114	kIPMBinNeedsConversion	IPM BIN needs conversion
-15113	kIPMEndOfBin	Internal error
-15112	kIPMBadQName	Invalid queue name
-15111	kIPMCorruptedBin	IPM BIN is damaged
-15110	kIPMBinBusy	Internal error
-15109	kIPMPortClosed	Stream closed
-15108	kIPMStreamErr	Error on stream
-15107	kIPMBlkNotFound	Specified block nonexistent

-15106	kIPMAttrNotInHdr	Specified attribute not in message header
-15105	kIPMInvalidFilter	Filter is invalid
-15104	kIPMNoRecipientsYet	Require recipient to send
-15103	kIPMInvalidSender	Sender is invalid
-15102	kIPMCacheFillError	Internal error
-15101	kIPMBlockIsNotNestedMsg	Block is not message (IPMOpenBlockAsMsg)
-15100	kIPMAbortOfNestedMsg	Canceled nested message
-15099	kIPMCorruptDataStructures	Message is corrupt
-15098	kIPMA1HdrCorrupt	Message is corrupt; may not be message
-15097	kIPMNestedMsgOpened	Nested message opened; cannot do operation
-15096	kIPMNotInABlock	Specified starting point not within the message
-15094	kIPMUpdateCatFailed	Internal error
-15093	kIPMInvalidOffset	Bad offset for read or write operation
-15092	kIPMInvalidProcHint	Process hint is invalid
-15091	kIPMInvalidMsgType	Message type is invalid; only kIPMOSFormatType allowed when creating a letter
-15090	kIPMCantCreateIPMCatEntry	Internal error
-15068	kMailBadState	Invalid status setting
-15066	kMailBadMSAM	MSAM unusable for unspecified reason
-15062	kMailNoSuchSlot	No such slot
-15061	kMailMalformedContent	Content data malformed
-15060	kMailBadSlotInfo	Invalid slot information
-15059	kMailMSAMSuspended	MSAM is suspended
-15058	kMailSlotSuspended	Slot is suspended
-15056	kMailNoMSAMErr	No such MSAM
-15055	kMailTooManyErr	IPM Manager or MSAM too busy to handle event
-15054	kMailLengthErr	Error occurred in sending the event
-15053	kMailIgnoredErr	MSAM ignored high-level event
-15047	kMailNotASlotInQ	Invalid value for a slot's incoming queue
-15046	kMailInvalidPostItVersion	Message summary is wrong version
-15045	kMailInvalidRequest	Reference number invalid with this request
-15044	kMailBadEnclLengthErr	Invalid data length
-15043	kMailHdrAttrMissing	Required attribute not added to message
-15041	kMailInvalidSeqNum	Invalid message sequence number
-15040	kMailInvalidOrder	Content already closed
-15020	kDETPropertyBusy	Specified property is being edited
-15019	kDETInvalidCallBack	Invalid callback
-15018	kDETInvalidReqFunction	Invalid callback routine selector
-15017	kDETCouldNotFindCustomView	Could not find custom view
-15016	kDETCouldNotFindMenuItem	Could not find menu item
-15015	kDETCouldNotRemoveMenuItem	Could not remove item from dynamic menu
-15014	kDETCouldNotAddMenuItem	Could not add item to menu
-15013	kDETNoSuchView	No view found with specified property number
-15012	kDETInfoPageNotOpen	Information page not open
-15011	kDETUnableToAccessProperty	Property could not be found
-15010	kDETInvalidDSSpec	Could not resolve DSSpec
-15009	kDETRequestedTypeUnavailable	Item could not be represented in the specified format
-15008	kDETUnableToGetCommandItemSpec	Unable to retrieve information about item (possibly out of memory)
-15007	kDETInvalidCommandItemNumber	

		Command item number out of range
-15006	kDETTargetNotAnAspect	Specified target object not an aspect
-15005	kDETInvalidTarget	Target selector invalid
-15004	kDETUnknownTargetSelector	Selector type in target selector invalid
-15003	kDETInvalidTargetDSSpec	DSSpec in target selector could not be resolved
-15002	kDETInvalidTargetFromNonAspect	Targeted item doesn't have an aspect
-15001	kDETInvalidTargetItemNumber	Item number in target selector out of range
-15000	kDETInvalidTargetAspectName	Could not find aspect named in target selector
-13005	pmRecvEndErr	During receive, Power Manager did not finish handshake
-13004	pmRecvStartErr	During receive, Power Manager did not start handshake
-13003	pmSendEndErr	During send, Power Manager did not finish handshake
-13002	pmSendStartErr	Power ManagerIC did not start handshake
-13001	pmReplyTOErr	Timed out waiting to begin reply handshake
-13000	pmBusyErr	Power ManagerIC stuck busy
-11005	pictureDataErr	Invalid picture data
-11004	colorsRequestedErr	Number out of range or greater than that passed to NewPictInfo
-11003	cantLoadPickMethodErr	Custom pick method not in resource chain
-11002	pictInfoVerbErr	Invalid verb combination specified
-11001	pictInfoIDErr	Invalid picture information ID
-11000	pictInfoVersionErr	Version number not 0
-9999	cannotMoveAttachedController	Cannot move attached controllers
-9998	controllerHasFixedHeight	Cannot change controller height
-9997	cannotSetWidthOfAttachedController	Cannot change controller width
-9996	controllerBoundsNotExact	Boundary rectangle not exact
-9995	editingNotAllowed	Controller does not support editing
-9994	badControllerHeight	Invalid height
-8998	errNotAKey	Key for desired font number and style could not be found in font table
-8997	errFaceListBad	Entry could not be found in typeface list
-8996	errSizeListBad	The size list contained an entry that could not be reconciled with the typeface list
-8995	errFontNotFound	Font query reply didn't match any fonts in list of PostScript names
-8994	errUnknownPSLevel	The PostScript level has an unknown value
-8993	errInLineTimeout	The printer is not responding
-8991	errNoProcSetRes	The resource describing needed procedure sets is unavailable for the PostScript prolog
-8990	errBadSpoolFileVersion	Bad version number in header of spool file
-8989	errCouldNotMakeNumberedFilename	Could not make a unique filename for the spool file
-8987	errPSFileName	PostScript file isn't named
-8986	errBitmapFontMissing	Unable to build bitmap for font

-8985	errDidNotDownloadFont	A PostScript outline could not be found for a PostScript font, and there is no associated 'sfnt' resource
-8984	errBadConverterIndex	When saving a spool file to disk, the value in the fileTypeIndex field had no matching entry in the driver
-8983	errSpoolFolderIsAFile	The spool folder is a file instead of a folder
-8982	errPSFileNameNull	The filename pointer for the spool file is null
-8981	errNullColorInfo	The getColor function called with null GetColorInfo handle
-8980	errNoPagesSpooled	Application called PrOpenDoc and PrCloseDoc without calling PrOpenPage and PrClosePage in between
-8979	errBadConverterID	The 'PDEF' converter doesn't exist
-8978	errNoPattern	The pixel pattern could not be found and could not be built
-8977	errPSStateUnderflow	PostScript stack underflow while restoring graphics state
-8976	errBadFontKeyType	Font found in printer is not Type 1, TrueType, or bitmapped font
-8973	codecOpenErr	Compressor or decompressor component could not be opened by the Image Compression Manager
-8972	codecConditionErr	Component cannot perform requested operation
-8971	codecExtensionNotFoundErr	Requested extension is not in the image description structure
-8971	scTypeNotFoundErr	Component does not have the information you want
-8970	codecDataVersErr	Compressor does not support the compression version used to compress the image
-8969	codecBadDataErr	Compressed data contains inconsistencies
-8968	codecWouldOffScreenErr	Compressor would use screen buffer if it could
-8967	codecAbortErr	Operation aborted by the progress function
-8966	codecSpoolErr	Error loading or unloading data
-8965	codecImageBufErr	Could not allocate the image buffer
-8964	codecScreenBufErr	Could not allocate the screen buffer
-8963	codecSizeErr	Invalid buffer size specified
-8962	codecUnimpErr	Feature not implemented by this compressor
-8961	noCodecErr	Image Compression Manager could not find specified error; Image Compression Manager could not find the specified compressor
-8960	codecErr	General error returned by compressor; can be returned by any function that gets handled by the compressor
-8160	zoomRangeErr	The print image enlarged by the user with the Page Setup dialog box overflows the available page resolution
-8133	generalPSErr	A PostScript error occurred during transmission of data to the printer; this is most often caused by a bug in the application-supplied PostScript code
-8132	manualFeedTOErr	A timeout occurred (that is, no communication has occurred with the printer for two minutes); this is usually caused by an extremely long imaging time or a dropped connection
-8131	[no name]	Printer not responding

-7934	scsiRequestAborted	Parameter block request aborted by the host
-7933	scsiUnableToAbort	Unable to abort parameter block request
-7932	scsiNonZeroStatus	The target returned non-zero status upon completion of the request
-7927	scsiUnableToTerminate	Unable to terminate I/O parameter block request
-7926	scsiSelectTimeout	Target selection timeout
-7925	scsiCommandTimeout	The timeout value for this parameter block was exceeded and the parameter block was aborted
-7924	scsiIdentifyMessageRejected	The target issued a REJECT message in response to the IDENTIFY message; the LUN probably does not exist
-7923	scsiMessageRejectReceived	REJECT message received
-7922	scsiSCSIBusReset	Execution of this parameter block was halted because of a SCSI bus reset
-7921	scsiParityError	An uncorrectable parity error occurred
-7920	scsiAutosenseFailed	Automatic REQUEST SENSE command failed
-7918	scsiDataRunError	Data overrun/underrun error
-7917	scsiUnexpectedBusFree	Unexpected bus free phase
-7916	scsiSequenceFail	Target bus phase sequence failure
-7915	scsiWrongDirection	Data phase was in an unexpected direction
-7913	scsiBDRsent	A SCSI bus device reset (BDR) message was sent to the target
-7912	scsiTerminated	Parameter block request terminated by the host
-7911	scsiNoNexus	Nexus is not established
-7910	scsiCDBReceived	The SCSI CDB was received
-7888	scsiTooManyBuses	SIM registration failed because the XPT registry is full
-7887	scsiBusy	SCSI subsystem is busy
-7886	scsiProvideFail	Unable to provide the requested service
-7885	scsiDeviceNotThere	SCSI device not installed or available
-7884	scsiNoHBA	No HBA detected
-7883	scsiDeviceConflict	Attempt to register more than one driver to a device
-7882	scsiNoSuchXref	No driver has been cross-referenced with this device
-7881	scsiQLinkInvalid	The qLink field was not 0
-7872	scsiPBLengthError	The parameter block length is too small for this SIM
-7871	scsiFunctionNotAvailable	The requested function is not supported by this SIM
-7870	scsiRequestInvalid	The parameter block request is invalid
-7869	scsiBusInvalid	The bus ID is invalid
-7868	scsiTIDInvalid	The target ID is invalid
-7867	scsiLUNInvalid	The logical unit number is invalid
-7866	scsiIDInvalid	The initiator ID is invalid
-7865	scsiDataTypeInvalid	SIM does not support the requested scsiDataType
-7864	scsiTransferTypeInvalid	The scsiTransferType is not supported by this SIM
-7863	scsiCDBLengthInvalid	The CDB length supplied is not supported by this SIM; typically this means it was too big
-5553	gestaltLocationErr	Function not in system heap
-5552	gestaltDupSelectorErr	Selector already exists
-5551	gestaltUndefSelectorErr	Undefined selector
-5550	gestaltUnknownErr	Could not obtain the response
-5502	envVersTooBig	Requested version of SysEnviron not available

-5501	envBadVers	Nonpositive version number passed
-5500	envNotPresent	SysEnviron trap not present
-5063	afpSameNodeErr	Attempt to log on to a server running on the same machine
-5062	afpAlreadyMounted	Volume already mounted
-5061	afpCantMountMoreSrvrs	Maximum number of volumes have been mounted
-5060	afpBadDirIDType	Not a fixed directory ID volume
-5043	afpInsideSharedErr	The directory is inside a shared directory
-5042	afpPwdExpired	Password has expired on server
-5039	afpBadIDErr	Bad file ID
-5038	afpSameObjectErr	Source and destination files are the same
-5037	afpCatalogChanged	Catalog has changed and search cannot be resumed
-5035	afpIDExists	File ID already exists
-5034	afpIDNotFound	File ID not found
-5033	afpContainsSharedErr	The directory contains a share point
-5030	afpIconTypeError	Sizes of new icon and one it replaces don't match
-5025	afpObjectTypeErr	Object is a directory, not a file; a directory exists with that name; this directory is not a share point
-5023	afpUserNotAuth	User authentication failed (usually, password is not correct)
-5021	afpRangeOverlap	User attempted to lock some or all of a range that is already locked
-5020	afpRangeNotLocked	User has attempted to unlock a range that was not locked by that user
-5019	afpParmError	The AFP command block size is equal to 0 (this error is also returned when the command block is equal to 0 or \$FF [255] or GetSrvrStatus [15])
-5016	afpNoServer	Server is not responding
-5015	afpNoMoreLocks	Byte range locking has failed because the server cannot lock any additional ranges
-5012	afpItemNotFound	Could not determine kind string; application information not found
-5006	afpDenyConflict	The operation has failed because the permission or deny mode conflicts with the mode in which the fork has already been opened
-5003	afpBadVersNum	Workstation is using an AFP version that the server doesn't recognize
-5002	afpBadUAM	User authentication method is unknown
-5000	afpAccessDenied	The operation has failed because the user does not have the correct access to the file or folder
-4101	PAPNoPrinter	The printer is not found, is closed, or is not selected
-4100	PAPConnClosed	The connection is closed
-4099	PAPTooBig	The write request is too big
-4098	PAPActive	The request is already active
-4097	PAPBadRefnum	Bad connection reference number
-4096	PAPNoCCBs	There are no free connect control blocks (CCBs) available
-3104	extractErr	Can't find tuple in buffer
-3102	noMPPErr	The .MPP driver is not installed
-3101	buf2SmallErr	Packet too large for buffer; partial data returned
-3032	noPrefAppErr	No translation preference available
-3031	badTranslationSpecErr	Translation path is invalid
-3030	noTranslationPathErr	Application cannot open document

-3027	noTransSysInstalledErr	No translation systems installed
-3025	invalidTranslationPathErr	howToTranslate is invalid
-3002	componentNotCaptured	This component has not been captured
-3001	validInstancesExist	This component has open connections
-3000	invalidComponentID	No component has this component identifier; speech channel is uninitialized or bad
-2824	fragInvalidFragmentUsage	Fragment is used invalidly
-2823	fragArchErr	Fragment targeted for unacceptable architecture
-2822	fragAppNotFound	No application found in 'cfrg' resource
-2821	fragUserInitProcErr	Initialization procedure did not return noErr
-2820	fragCorruptErr	Fragment container is corrupted
-2819	fragConstErr	Internal inconsistency discovered
-2818	fragMgrInitErr	Error during Code Fragment Manager initialization
-2817	fragLibConnErr	Error connecting to library
-2816	fragInitRtnUsageErr	Boot library has initialization routine
-2815	fragInitLoop	Circularity in required initialization order
-2814	fragImportTooNew	Import library is too new
-2813	fragImportTooOld	Import library is too old
-2812	fragObjectInitSeqErr	Order error during user initialization function
-2811	fragNoContextIDs	No more context IDs available
-2810	fragNoAddrSpace	Not enough memory in user's address space for section
-2809	fragNoMem	Not enough memory for internal bookkeeping
-2807	fragHadUnresolveds	Loaded fragment has unacceptable unresolved symbols
-2806	fragFormatUnknown	Fragment container format unknown
-2805	fragDupRegLibName	Registered name already in use
-2804	fragLibNotFound	Library name not found in fragment registry
-2803	fragSectionNotFound	Section was not found
-2802	fragSymbolNotFound	Symbol was not found in connection
-2801	fragConnectionIDNotFound	Connection ID is not valid
-2800	fragContextNotFound	Context ID is not valid
-2519	tsmUnknownErr	Any other error
-2518	tsmUnsupportedTypeErr	Unsupported interface type
-2517	tsmScriptHasNoIMErr	Script has no (or old) input method
-2516	tsmInputMethodIsOldErr	The default input method is old-style
-2515	tsmComponentAlreadyOpenErr	Text service component already open for document
-2514	tsmTSNotOpenErr	Text service component is not open
-2513	tsmTSHasNoMenuErr	The text service component has no menu
-2512	tsmUseInputWindowErr	An input window is being used
-2511	tsmDocumentOpenErr	There are open documents
-2510	tsmTextServiceNotFoundErr	No text service component found
-2509	tsmCantOpenComponentErr	Can't open the component
-2508	tsmNoOpenTSErr	There is no open text service component
-2507	tsmDocNotActiveErr	Document is not active
-2506	tsmTSMDocBusyErr	Document is still active
-2505	tsmInvalidDocIDErr	Invalid TSM document ID
-2504	tsmNeverRegisteredErr	The caller is not TSM-aware
-2503	tsmAlreadyRegisteredErr	The caller is already TSM-initialized
-2502	tsmNotAnAppErr	The caller was not an application
-2501	tsmInputMethodNotFoundErr	Specified input method cannot be found
-2500	tsmUnsupScriptLanguageErr	Specified script and language are not supported
-2053	featureUnsupported	Movie Toolbox does not support this feature

-2052	couldNotUseAnExistingSample	Movie Toolbox could not use a sample
-2051	noDefaultDataRef	Could not find a default data reference
-2050	badDataRefIndex	Data reference index value is invalid
-2049	invalidDataRefContainer	Invalid data reference
-2048	noMovieFound	Toolbox cannot find a movie in the movie file
-2047	dataNoDataRef	No data reference value found
-2046	endOfDataReached	End of data
-2045	dataAlreadyClosed	You have already closed this data source
-2044	dataAlreadyOpenForWrite	Data source is already open for write
-2043	dataNotOpenForWrite	Cannot write to this data source
-2042	dataNotOpenForRead	Cannot read from this data source
-2041	invalidSampleDescription	This sample description is invalid or corrupted
-2040	invalidChunkCache	The chunk cache is corrupted
-2039	invalidSampleDescIndex	Sample description index value invalid
-2038	invalidChunkNum	There is no chunk with this chunk number
-2037	invalidSampleNum	There is no sample with this sample number
-2036	invalidRect	Specified rectangle has invalid coordinates
-2035	cantEnableTrack	Cannot enable this track
-2034	internalQuickTimeError	Internal error
-2033	badEditIndex	This edit index value is not valid
-2032	timeNotInMedia	This time value is outside of this media
-2031	timeNotInTrack	This time value is outside of this track
-2030	trackNotInMovie	This track is not in this movie
-2029	trackIDNotFound	Cannot locate a track with this ID value
-2028	badTrackIndex	This track index value is not valid
-2027	maxSizeToGrowTooSmall	Maximum size must be larger
-2026	userDataItemNotFound	Cannot locate this user data item
-2025	staleEditState	Movie or track has been disposed
-2024	nonMatchingEditState	This edit state is not valid for this movie
-2023	invalidEditState	This edit state is invalid
-2022	cantCreateSingleForkFile	Error trying to create a single-fork file—this occurs when the file already exists
-2021	wfFileNotFound	Cannot locate this file
-2020	movieToolboxUninitialized	You haven't initialized the Movie Toolbox
-2019	progressProcAborted	Your progress procedure returned an error
-2018	mediaTypesDontMatch	These media don't match
-2017	badEditList	The track's edit list is corrupted
-2016	cantPutPublicMovieAtom	Cannot write to this movie file
-2015	invalidTime	This time value is invalid
-2014	invalidDuration	This duration value is invalid
-2013	invalidHandler	This handler is invalid
-2012	invalidDataRef	This data reference is invalid
-2011	invalidSampleTable	This sample table is corrupted or invalid
-2010	invalidMovie	This movie is corrupted or invalid
-2009	invalidTrack	This track is corrupted or invalid
-2008	invalidMedia	This media is corrupted or invalid
-2007	noDataHandler	Media has no data handler
-2006	noMediaHandler	Media has no media handler
-2005	badComponentType	Component cannot accommodate this data
-2004	cantOpenHandler	Cannot open this handler
-2003	cantFindHandler	Cannot locate this handler
-2002	badPublicMovieAtom	Movie file corrupted

-2001	badImageDescription	Problem with this image description
-2000	couldNotResolveDataRef	Cannot use this data reference
-1983	kSIGNoSignature	Standard file signature not found
-1982	kSIGSignerNotValidErr	Signer file has either expired or is not yet valid
-1981	kSIGConversionErr	Unable to convert an attribute to Macintosh format
-1980	kSIGNoDigestErr	No digest in the signature
-1979	kSIGContextPrepareErr	Context either corrupted or already prepared with SIGVerifyPrepare, SIGSignPrepare, or SIGDigestPrepare
-1978	kSIGToolboxNotPresentErr	For servers; not returned by the toolbox
-1977	kSIGInternalsErr	Bad digest, context, or signature
-1976	kSIGPasswordErr	Password is incorrect
-1975	kSIGSignerErr	Problem with the signer file or signature
-1974	kSIGIndexErr	Index given is outside the range of allowable values
-1973	kSIGInvalidCredentialErr	Verified OK but credential either pending or expired
-1972	kSIGVerifyFailedErr	Verification failed
-1971	kSIGCertificateQueryDenied	Can't query certificates with this context
-1970	kSIGOperationIncompatibleErr	Context in use for different type of operation
-1953	kSDPPersonalDirectoryRepairFailed	Cannot sort personal catalog
-1952	kSDPNoSelection	No selection is in Catalog-Browsing panel
-1951	kSDPTooManyLoginAttempts	User tried more than 3 incorrect passwords
-1950	kSDPNoSearchText	No text is in Find panel text field
-1928	kSMPTTooManyEnclosures	More than 50 total files and folders
-1927	kSMPTTooManyPages	Image is more than 127 pages
-1926	kSMPPParamCountErr	Enclosure count should be 1
-1925	kSMPSubjectTooBig	Subject string exceeds 127 characters
-1924	kSMPIInvalidAddressString	Address string is invalid
-1923	kSMPIIllegalSendFormats	Format is not in canSend parameter
-1922	kSMPIAddressAlreadyInList	Specified address is in Recipients field
-1921	kSMPIRecordDoesNotContainAddress	Address is not in this record
-1920	kSMPIComponentIsAlreadyTarget	The selected field is the target
-1919	kSMPIMailerAlreadyNotTarget	This mailer is not the target
-1918	kSMPIIllegalComponent	Bad field name parameter
-1917	kSMPIMailerAlreadyExpandedOrContracted	Mailer is already in requested state
-1916	kSMPIMailerCannotExpandOrContract	Mailer created with canContract false
-1915	kSMPIIllegalForDraftLetter	Operation cannot be completed
-1914	kSMPICannotSendReceivedLetter	Letter is received; cannot be sent
-1913	kSMPINoMatchingBegin	End function called without begin
-1912	kSMPIMailerUneditable	Mailer cannot be edited
-1911	kSMPIMailerAlreadyInWindow	A mailer was previously allocated
-1910	kSMPINoSuchAddress	Requested address not found
-1909	kSMPINoMailerInWindow	No mailer is in specified window
-1908	kSMPICommandDisabled	Requested command unavailable
-1907	kSMPIFinderNotRunning	The Finder is not running
-1906	kSMPIHasOpenAttachments	One or more enclosures are open
-1905	kSMPINoNextLetter	There is no next letter in In Tray

-1904	kSMPMailboxNotFound	Cannot find mailbox
-1903	kSMPShouldNotAddContent	You cannot add content to letter
-1902	kSMPMailerNotInitialized	Mailer has not been initialized
-1901	kSMPCopyInProgress	Enclosure being copied to mailer
-1900	kSMPNotEnoughMemoryForAllRecipients	Too many recipients in mailer
-1762	errOSACantOpenComponent	Generic scripting component error; can't connect to scripting component
-1761	errOSAComponentMismatch	Generic scripting component error; parameters are for two different scripting components instead of the same one
-1759	errOSADataFormatTooNew	Data format is too new
-1758	errOSADataFormatObsolete	Data format is obsolete
-1757	errOSANoSuchDialect	Invalid dialect code
-1756	errOSASourceNotAvailable	Source data not available
-1754	errOSABadSelector	Selector not supported by scripting component
-1753	errOSAScriptError	Error occurred during compilation or execution
-1752	errOSABadStorageType	Illegal storage type
-1751	errOSAIInvalidID	Invalid script ID
-1750	errOSASystemError	General scripting system error
-1732	errAERecordingIsAlreadyOn	Attempt to turn recording on when it is already on
-1731	errAEUnknownObjectType	Descriptor type of token returned by AEResolve is not known to server application
-1730	errAEEmptyListContainer	The container for an Apple event object is specified by an empty list
-1729	errAENegativeCount	Object-counting function returned negative value
-1728	errAENoSuchObject	A run-time resolution error, for example: object specifier record asked for the third element, but there are only two
-1727	errAENotAnObjectSpec	The objSpecifier parameter of AEResolve is not an object specifier record
-1726	errAEBadTestKey	The descriptor record in a test key is neither a comparison descriptor record nor a logical descriptor record
-1725	errAENoSuchLogical	The logical operator in a logical descriptor record is not kAEAND, kAEOR, or kAENOT
-1723	errAEAccessorNotFound	There is no object accessor function for the specified object class and token descriptor type
-1721	errAEWrongNumberArgs	The number of operands provided for the kAENot logical operator is not 1
-1720	errAEImpossibleRange	The range is not valid because it is impossible for a range to include the first and last objects that were specified; an example is a range in which the offset of the first object is greater than the offset of the last object
-1719	errAEIllegalIndex	Not a valid list index
-1718	errAEReplyNotArrived	Reply has not yet arrived
-1717	errAEHandlerNotFound	No handler found for an Apple event or a coercion, or no object callback function found
-1716	errAEUnknownAddressType	Unknown Apple event address type
-1715	errAEParamMissed	Handler cannot understand a parameter the client considers required
-1714	errAENotASpecialFunction	The keyword is not valid for a special function

-1713	errAENoUserInteraction	No user interaction allowed
-1712	errAETimeout	Apple event timed out
-1711	errAEWaitCanceled	User canceled out of wait loop for reply or receipt
-1710	errAEUnknownSendMode	Invalid sending mode was passed
-1709	errAEReplyNotValid	AEResetTimer was passed an invalid reply
-1708	errAEEventNotHandled	Event wasn't handled by an Apple event handler
-1707	errAENotAppleEvent	Event is not an Apple event
-1706	errAENewerVersion	Need a newer version of the Apple Event Manager
-1704	errAENotAEDesc	Not a valid descriptor record
-1703	errAEWrongDataType	Wrong descriptor type
-1702	errAECorruptData	Data in an Apple event could not be read
-1702	errOSACorruptData	Same as errAECorruptData
-1701	errAEDescNotFound	Descriptor record was not found
-1700	errAEC coercionFail	Data could not be coerced to the requested descriptor type
-1700	errOSACantCoerce	Same as errAEC coercionFail; data could not be coerced to the requested data type
-1646	kOCEDirectoryCorrupt	Serious disk fill corruption problem
-1645	kOCERLIsDontMatch	RLIs of different records in the record list are not the same
-1644	kOCENoSuchIcon	There is no matching icon from OCEGetDirectoryIcon
-1643	kOCEMiscError	Miscellaneous error
-1642	kOCENoSuchAttributeType	Can't find specified attribute type
-1641	kOCENoDupAllowed	Duplicate record name and type
-1640	kOCEMoreAttrValue	Buffer too small for a single attribute value
-1639	kOCESBadStartingAttribute	Starting attribute index is not within range
-1638	kOCESBadStartingRecord	Starting record index out of range
-1637	kOCESLengthError	The supplied buffer was too small
-1636	kOCESAMRecordExists	CSAM record is already in Setup catalog
-1635	kOCESAMNotInstantiated	CSAM is not instantiated
-1634	kOCESAMRecordNotFound	CSAM Record not found
-1633	kOCESOCESetupRequired	LocalIdentity Setup is required; local identity is not set up
-1632	kOCESAborted	The call was aborted
-1631	kOCESAbortNotSupportedForThisCall	Abort not supported
-1630	kOCESDirectoryNotFoundErr	Catalog was not found in the list
-1629	kOCESDirListFullErr	The catalog list is full; try removing an entry
-1628	kOCESAMInstallErr	CSAM could not be installed or doesn't exist
-1627	kOCESPABNotOpen	The specified personal catalog is not open to make the operation
-1626	kOCESOperationNotSupported	The specified catalog does not support this operation
-1625	kOCESStreamCreationErr	Error in creating connection to server; error occurred in creating the stream
-1624	kOCESRefNumBad	RefNum is not valid
-1623	kOCESMoreData	Buffer was too small to hold all available data; more data available
-1622	kOCESTypeExists	The type already exists in the record
-1621	kOCESAttributeValueTooBig	Attribute value is larger than kAttrValueMaxBytes bytes
-1620	kOCENoSuchPseudonym	The specified pseudonym does not exist

-1619	koCENoSuchAttributeValue	Can't find specified attribute value
-1618	koCENoSuchRecord	Can't find specified record
-1617	koCEBadRecordID	Record name or record type doesn't match creation ID
-1616	koCEDNodeUnavailable	Could not find any servers that serve the requested dNode
-1615	koCENoSuchDNode	Can't find specified dNode
-1614	koCEBogusArgs	Args not formatted correctly on the wire
-1613	koCETargetDirectoryInaccessible	Target catalog is not currently available; catalog server not responding
-1612	koCEDatabaseFull	The disk is full
-1611	koCETooBusy	Server cannot complete call at this time
-1610	koCENotLocal	The server does not serve the requested dNode; internal AOCE error
-1571	koCEAuthenticationTrouble	Authentication process failed; reply incorrect for the challenge sent
-1570	koCENoASDSPWorkSpace	No ASDSP workspace passed; you passed NIL for the workspace parameter
-1569	koCEAmbiguousMatches	Ambiguous matches found in resolving CIDs
-1568	koCEOperationDenied	Local identity operation denied
-1567	koCEUnknownID	Authentication identity is not valid
-1566	koCENoMoreIDs	Identity table is full
-1565	koCENotLocalIdentity	You cannot unbind a local identity
-1564	koCEDirectoryIdentitySetupDoesNotExist	Catalog has not been set up
-1563	koCEDirectoryIdentitySetupExists	Catalog has already been set up
-1562	koCELocalIdentitySetupExists	Local identity setup exists, use AuthChangeLocalIdentity instead
-1561	koCELocalAuthenticationFail	User hasn't entered Key Chain password; local identity locked
-1560	koCELocalIdentityDoesNotExist	Local identity has not been set up
-1559	koCEBadEncryptionMethod	During the authentication process, the ASDSP implementations could not agree on an encryption method to be used (ASDSP can support multiple stream encryption methods. In Release 1, only RC4 and "no encryption" are supported.)
-1558	koCEInitiatorKeyProblem	No key, or initiator's key changed
-1557	koCEWrongIdentityOrKey	Incorrect key for client
-1556	koCEUndesirableKey	Password too short or resulting key is undesirable
-1555	koCEMalFormedKey	Key not derived properly from password
-1554	koCEKeyAlreadyRegistered	A key already exists
-1553	koCEAgentKeyNotFound	Intermediary's key not found
-1552	koCERecipientKeyNotFound	The recipient key was not found
-1551	koCEPrincipalKeyNotFound	Couldn't decode proxy because principal has no key
-1550	koCENoKeyFound	No key was found
-1549	koCEDisallowedRecipient	Recipient record ID does not appear in proxy
-1548	koCEProxyExpired	Current time is later than proxy expiration time
-1547	koCEProxyImmature	Proxy not yet valid

-1546	koCECredentialsExpired	Current time is later than credentials expiration time
-1545	koCECredentialsImmature	Credentials not yet valid
-1544	koCECredentialsProblem	Couldn't decrypt credentials
-1543	koCEUnsupportedCredentialsVersion	Credentials version not supported
-1542	koCEAccessRightsInsufficient	Stream needs to be authenticated, or not authorized, or someone other than agent trying to TPF, or problem in server-to-server authentication
-1541	koCEWriteAccessDenied	Identity lacks write access privileges
-1540	koCEReadAccessDenied	Identity lacks read access privileges
-1516	koCERefIsClosing	IPM Manager is shutting down the personal MSAM, or server MSAM's mail server is shutting down
-1514	koCEInvalidRecipient	Bad recipient
-1513	koCEConnectionClosed	Network connection has closed
-1511	kIPMMsgTypeReserved	Message creator and/or type specified not allowed
-1510	koCEAlreadyExists	Catalog with same name and kind already exists; duplicate recipient type
-1506	koCEInternalErr	Serious internal error
-1504	koCEVersionErr	Need to sort personal catalog; wrong version of nested message
-1503	koCEBufferTooSmall	Buffer too small for data requested
-1502	koCEInvalidRef	Invalid message reference number
-1500	koCEToolboxNotOpen	Collaboration toolbox is shutting down
-1306	sameFileErr	Source and destination files are the same
-1305	desktopDamagedErr	The desktop database has become corrupted—the Finder will fix this, but if your application is not running with the Finder, use PBDTReset or PBDTDelete
-1304	catChangedErr	Catalog has changed and catalog position record may be invalid
-1303	diffVolErr	Files are on different volumes
-1302	notAFileErr	Specified file is a directory
-1301	fidExists	File ID already exists
-1300	fidNotFoundErr	File ID not found
-1280	errRefNum	Bad connection reference number
-1279	errAborted	Request aborted by dspRemove or dspClose routine
-1278	errState	Bad connection state for this operation
-1277	errOpening	Attempt to open connection failed
-1276	errAttention	Attention message too long
-1275	errFwdReset	Read terminated by forward reset
-1274	errDSPQueueSize	Send or receive queue is too small
-1273	errOpenDenied	Open request denied by recipient
-1105	reqAborted	
-1104	noDataArea	Too many outstanding ATP calls
-1103	noSendResp	PAddResponse issued before PSendResponse
-1102	cbNotFound	ERead not active; NBP queue element not found; the aKillQEl parameter does not point to a PSendRequest or PNSendRequest queue element
-1101	noRelErr	No release received; timer expired before MSAM responded

-1100	badBuffNum	Sequence number out of range
-1099	badATPSkt	Bad responding socket
-1098	tooManySkts	Too many responding sockets
-1097	tooManyReqs	Too many concurrent requests; wait a few minutes, then try the request again
-1096	reqFailed	Request to contact router failed; retry count exceeded
-1073	aspSizeErr	The size of the command block exceeds the maximum size of aspMaxCmdSize
-1072	aspSessClosed	The .XPP driver is in the process of closing the session
-1071	aspServerBusy	
-1070	aspParamErr	
-1069	aspNoServers	
-1068	aspNoMoreSess	
-1067	aspBufTooSmall	
-1066	aspBadVersNum	The server cannot support the ASP version number
-1028	nbpNotFound	Name not found
-1027	nbpDuplicate	Location name represents a duplicate on this computer
-1026	nbpConfDiff	Name confirmed for different socket
-1025	nbpNoConfirm	Name not confirmed
-1023	noMoreMultiNodes	No node address is available on the network
-1022	mnNotSupported	Multinode is not supported by the current AppleTalk connection file of type 'adev'
-1021	tryAddNodeAgainErr	The .MPP driver was not able to add node; try again
-1000	noMaskFoundErr	Cannot find or create mask for the icon family
-932	guestNotAllowedErr	Destination port requires authentication
-931	badLocNameErr	Location name is invalid
-930	badServiceMethodErr	Service method is other than ppcServiceRealTime
-928	noUserRecErr	Invalid user reference number
-927	authFailErr	User's password is wrong
-926	noInformErr	PPCStart failed because target application did not have an inform pending
-925	networkErr	An error has occurred in the network
-924	noUserRefErr	Unable to create a new user reference number
-923	notLoggedInErr	Default user reference number does not yet exist
-922	noDefaultUserErr	User has not specified owner name in Sharing Setup control panel
-919	badPortNameErr	PPC port record is invalid
-917	sessClosedErr	The kAEDontReconnect flag in the sendMode parameter was set, and the server quit and then restarted; the session has closed
-916	portClosedErr	The port was closed
-915	noResponseErr	Unable to contact application
-912	userRejectErr	Destination rejected the session request
-911	noUserNameErr	User name unknown on destination machine
-910	portNameExistsErr	Another port is already open with this name
-909	badReqErr	Bad parameter or invalid state for this operation
-908	noSessionErr	Invalid session reference number
-907	sessTableErr	PPC Toolbox is unable to create a session

-906	destPortErr	Port does not exist at destination; or, server hasn't set 'SIZE' resource to indicate awareness of high-level events, or else is not present
-905	localOnlyErr	Network activity is currently disabled
-904	noGlobalsErr	System unable to allocate memory, critical error
-903	noPortErr	Client hasn't set 'SIZE' resource to indicate awareness of high-level events; unable to open port; bad port reference number; invalid port name
-902	nameTypeErr	Invalid or inappropriate locationKindSelector in location name
-900	notInitErr	PPC Toolbox has not been initialized yet
-863	hmCloseViewActive	Balloon can't be removed because Close View is in use
-862	hmNoBalloonUp	No balloon showing
-861	hmOperationUnsupported	Invalid value passed in the method parameter
-859	hmUnknownHelpType	Help message record contained a bad type
-858	hmWrongVersion	Wrong version of Help Manager resource
-857	hmSkippedBalloon	No help message to fill in
-855	hmHelpManagerNotInitd	Help menu not set up
-854	hmSameAsLastBalloon	Menu and item are same as previous menu and item
-853	hmBalloonAborted	Because of constant cursor movement, the help balloon wasn't displayed
-850	hmHelpDisabled	Help balloons are not enabled
-813	rcDBPackNotInitd	The InitDBPack function has not yet been called
-812	rcDBWrongVersion	Wrong version number
-811	rcDBNoHandler	There is no handler for this data type installed for the current application
-810	rcDBBadAsynchPB	Invalid parameter block specified
-809	rcDBAsynchNotSupp	The database extension does not support asynchronous calls
-808	rcDBBadDDev	Couldn't find the specified database extension, or error occurred in opening database extension
-807	rcDBBadSessNum	Invalid session number
-806	rcDBBadSessID	Session ID is invalid
-805	rcDBExec	Query currently executing
-804	rcDBBreak	Function timed out
-803	rcDBBadType	Next data item not of requested data type
-802	rcDBError	Error executing function
-801	rcDBValue	Data available or successfully retrieved
-800	rcDBNull	The data item was NULL
-625	cannotDeferErr	Unable to defer additional user functions
-624	interruptsMaskedErr	Called with interrupts masked
-623	notLockedErr	Specified range of memory is not locked
-622	cannotMakeContiguousErr	Cannot make specified range contiguous
-621	notHeldErr	Specified range of memory is not held
-620	notEnoughMemoryErr	Insufficient physical memory
-610	noUserInteractionAllowed	Background application sends event requiring authentication; cannot interact directly with user
-609	connectionInvalid	Connection is invalid; nonexistent signature or session ID
-608	noOutstandingHLE	No outstanding high-level event
-607	bufferIsSmall	Buffer is too small
-606	appIsDaemon	Application is background-only

-605	appMemFullErr	Partition size specified in 'SIZE' resource is not big enough for launch
-602	appModeErr	Addressing mode is 32-bit, but application is not 32-bit clean
-601	memFragErr	Not enough room to launch application with special requirements
-600	procNotFound	No eligible process with specified process serial number
-502	hwParamErr	Processor does not support flushing a range
-500	rgnTooBigErr	Bitmap would convert to a region greater than 64 KB
-463	notThePublisherWrn	Not the publisher
-461	containerNotFoundWrn	Alias was not resolved
-460	multiplePublisherWrn	Already is a publisher
-454	badSubPartErr	Bad edition container spec or invalid edition container
-452	notRegisteredSectionErr	Not registered
-451	badSectionErr	Not a valid section type
-450	editionMgrInitErr	Manager not initialized or could not load package
-416	btKeyLenErr	Key length too great or equal to zero
-415	btRecNotFnd	Record cannot be found
-414	btDupRecErr	Record already exists
-413	btNoSpace	Insufficient disk space to store dictionary
-410	notBTree	File is not a dictionary
-360	slotNumErr	Invalid slot number
-351	smRecNotFnd	Record not found in the slot resource table
-347	smByteLanesErr	Bad spByteLanes value
-346	smBadsPtrErr	Bad spsPointer value
-344	smNoMoresRsrcs	Requested sResource not found
-342	smGetDrvrNamErr	An error occurred during execution of _sGetDrvrName
-341	smCkStatusErr	Status of slot is bad
-338	smSelOOBErr	Selector out of bounds or function not implemented
-337	smSlotOOBErr	The given slot was out of bounds or does not exist
-336	smNilsBlockErr	The physical block size of an sBlock was zero
-335	smsPointerNil	The spsPointer value is NIL: no list is specified
-334	smCPUErr	The CPU field of the code to be executed by sExec was wrong
-333	smCodeRevErr	The revision of the code to be executed by sExec was wrong
-332	smReservedErr	A reserved field was not zero
-331	smBadsList	The IDs are not in ascending order
-330	smBadRefId	Reference ID was not found in the given list
-316	smInitStatVErr	The InitStatusV field was negative after PrimaryInit
-315	smNoBoardId	There is no board ID
-313	smNoBoardsRsrc	There is no board sResource
-312	smDisposePErr	An error occurred during execution of DisposePtr
-309	smBLFieldBad	A valid fhByteLanes field was not found
-308	smUnExBusErr	A bus error occurred
-302	smFormatErr	The format of the declaration ROM is wrong
-301	smCRCFail	CRC check failed
-300	smEmptySlot	No card in this slot

-299	nmTypeErr	Invalid qType value (must be ORD(nmType))
-252	badParmCount	Incorrect number of embedded command arguments
-250	badVoiceID	Specified voice has not been preloaded
-248	unimplMsg	Unimplemented message
-247	badPhonemeText	Raw phoneme text contains invalid characters
-246	badDictFormat	Pronunciation dictionary format error
-245	incompatibleVoice	Specified voice cannot be used with synthesizer
-244	voiceNotFound	Voice resource not found
-243	bufTooSmall	Output buffer is too small to hold result
-242	synthNotReady	Speech synthesizer is still busy speaking
-241	synthOpenFailed	Could not open another speech synthesizer channel
-240	noSynthFound	Could not find the specified speech synthesizer
-232	siUnknownQuality	Unknown quality
-231	siUnknownInfoType	Feature not implemented on synthesizer; unknown type of information
-230	siInputDeviceErr	Input device hardware failure
-229	siBadRefNum	Invalid reference number
-228	siBadDeviceName	Invalid device name
-227	siDeviceBusyErr	Sound input device is busy
-226	siInvalidSampleSize	Invalid sample size
-225	siInvalidSampleRate	Invalid sample rate
-224	siHardDriveTooSlow	Hard drive too slow to record
-223	siInvalidCompression	Invalid compression type
-222	siNoBufferSpecified	No buffer specified
-221	siBadSoundInDevice	Invalid sound input device
-220	siNoSoundInHardware	No sound input hardware available
-212	noMoreRealTime	Not enough CPU time available
-211	channelNotBusy	Channel not currently used
-210	buffersTooSmall	Buffer is too small
-209	channelBusy	Channel is busy
-208	badFileFormat	File is corrupt or unusable, or not AIFF or AIFF-C
-207	notEnoughBufferSpace	Insufficient memory available
-206	badFormat	Resource is corrupt or unusable
-205	badChannel	Channel is corrupt or unusable
-204	resProblem	Problem loading the resource
-203	queueFull	No room in the queue
-201	notEnoughHardwareErr	Insufficient hardware available
-200	noHardwareErr	Required sound hardware not available
-199	mapReadErr	Map inconsistent with operation
-198	resAttrErr	Attribute inconsistent with operation
-196	rmvResFailed	RemoveResource procedure failed
-194	addResFailed	AddResource procedure failed
-193	resFNotFound	Resource file not found
-192	resNotFound	Resource not found; unable to read resource; the current printer driver does not support PrGeneral—you should clear this error with a call to PrSetError with a parameter value of 0 (otherwise, PrError might still contain this error next time you check it)
-190	inputOutOfBounds	Offset or count out of bounds
-189	writingPastEnd	Writing past end of file
-188	resourceInMemory	Resource already in memory

-157	cDepthErr	Invalid pixel depth
-156	cResErr	Invalid resolution for MakeITable
-155	cDevErr	Invalid type of graphics device
-154	cProtectErr	ColorTable record entry protection violation
-153	cRangeErr	Range error on color table request
-152	cNoMemErr	Failed to allocate memory for structure
-151	cTempMemErr	Failed to allocate memory for temporary structures
-150	cMatchErr	Color2Index failed to find an index
-149	nsStackErr	Insufficient stack
-148	pixmapTooDeepErr	Pixel map is deeper than 1 bit per pixel
-147	regionTooBigError	Region too big or complex
-145	noMemForPictPlaybackErr	Insufficient memory for drawing the picture
-144	[no name]	Ran out of stack space while drawing polygon
-143	[no name]	CopyBits couldn't allocate required temporary memory
-128	userCanceledErr	User canceled an operation (e.g., translation, query); user clicked Cancel in dialog box; user decided not to conduct a session
-128	usrCanceledErr	The user canceled the operation
-127	fsDSIntErr	Internal file system error
-124	volGoneErr	Server volume has been disconnected
-123	wrgVolTypErr	Not an HFS volume; volume does not support Desktop Manager
-122	badMovErr	Attempted to move into offspring
-121	tmwdoErr	Too many working directories open
-120	dirNFErr	Directory not found or incomplete pathname
-117	memLockedErr	Block is locked
-115	memBCErr	Block check failed
-112	memPurErr	Attempt to purge a locked block
-111	memWZErr	Attempt to operate on a free block
-109	nilHandleErr	Handle argument is NIL; NIL master pointer
-108	iMemFullErr	There is not enough room in the heap zone
-108	memFullErr	Insufficient memory available; not enough memory to allocate the partition size specified in the 'SIZE' resource
-102	noTypeErr	Format not available; no data of the requested scrap format type in scrap; unrecognized file type
-100	noScrapErr	Scrap does not exist (not initialized)
-99	memROZErr	Operation on a read-only zone
-98	portNotCf	Driver open error code indicating that the parameter RAM is not configured for this connection; port is not configured
-97	portInUse	Driver open error code indicating that the port is in use
-95	excessCollsns	Hardware error; excessive collisions on write
-94	LAPProtErr	No protocol handler is attached
-93	noBridgeErr	Could not find router to forward packet
-92	ddpLenErr	Datagram is too long
-92	eLenErr	Packet too large or first entry of the write-data structure did not contain the full 14-byte header
-91	ddpSktErr	Error opening socket; bad socket number or socket table is full
-91	eMultiErr	Address not found

-88	prInitErr	Validity status is not \$A8
-87	prWrErr	Parameter RAM written did not verify
-86	clkWrErr	Time written did not verify
-85	clkRdErr	Unable to read clock
-84	firstDskErr	First of the range of low-level disk errors
-64	lastDskErr	Last of the range of low-level disk errors
-61	wrPermErr	Read/write permission doesn't allow writing; not a publisher
-60	badMDBErr	Bad master directory block
-59	fsRnErr	Problem during rename
-58	extFSErr	Disk has external file system—file system identifier is nonzero; volume belongs to an external file system
-57	noMacDskErr	Volume lacks Macintosh-format directory
-56	nsDrvErr	Specified drive number doesn't match any number in the drive queue
-55	volOnLinErr	Volume is already online
-54	permErr	Attempt to open locked file for writing; not a subscriber
-53	volOfflinErr	Volume is offline
-52	gfpErr	Error during GetFPos
-51	rfNumErr	Reference number invalid; reference number specifies nonexistent access path; bad working directory reference number
-50	kOCEParamErr	Invalid parameter
-50	paramErr	Drive number specified is bad; error in parameter list; invalid parameter (for example, value of handler pointer is NIL or odd); use PBDTGetPath; process serial number is invalid
-49	opWrErr	File already open with write permission
-48	dupFNErr	A file with the specified name already exists; file found instead of folder
-47	fBsyErr	File is busy; one or more files are open; directory not empty or working directory control block is open; section doing I/O
-46	vLckdErr	Volume is locked through software
-45	fLckdErr	File is locked; publisher writing to an edition
-44	wPrErr	Disk is write-protected; volume is locked through hardware
-43	fnfErr	File, directory, or edition container not found; target not found, but volume and parent directory found; for FindFolder: type not found in 'fld#' resource, or disk doesn't have System Folder support or System Folder in volume header, or disk does not have desktop database support for Desktop Folder—in all cases, folder not found; for ResolveAliasFile: target not found, but volume and parent directory found and theSpec parameter contains a valid file system specification record
-42	tmfoErr	Too many files open
-40	posErr	Attempt to position mark before start of file
-39	eofErr	Logical end-of-file reached; no additional data in the format

-38	fnOpnErr	File not open
-37	bdNamErr	Bad filename or volume name (perhaps zero length)
-36	ioErr	I/O error; data does not match in read-verify mode
-35	nsvErr	Volume not found
-34	dskFulErr	All allocation blocks on the volume are full; not enough disk space to translate file
-33	dirFulErr	File directory full
-28	notOpenErr	AppleTalk is not open; driver not open
-27	abortErr	Asynchronous recording was cancelled; publisher has written a new edition; request aborted by KillIO
-27	iIOAbort	I/O error
-26	dInstErr	Driver resource not found
-25	dRemovErr	Attempt to remove an open driver
-24	closErr	Driver unable to complete close request
-23	openErr	Unable to open device driver; requested read/write permission does not match driver's open permission
-22	unitEmptyErr	Driver reference number specifies a nil handle in unit table
-21	badUnitErr	Driver reference number does not match unit table
-20	writErr	Driver does not respond to write requests
-19	readErr	Driver does not respond to read requests
-18	statusErr	Driver does not respond to this status request
-17	controlErr	Driver does not respond to this control request; unimplemented control instructions—the Device Manager returns this result code
-3	corErr	PowerShare mail server not running
-2	vTypeErr	Invalid qType value (must be ORD(dtQType)); invalid qType value (must be ORD(vType))
-1	errADBop	Unsuccessful completion
-1	iPrSavPFil	Problem saving print file
-1	qErr	Entry is not in specified queue; queue element not found
0	fragNoErr	No error
0	no_draw_error	No error in drawing
0	noErr	No error
0	toggleUndefined	Undefined error
0	tsmComponentNoErr	Component result: no error
1	[no name]	User canceled initializing
1	noSuchRsl	Resolution requested with the PrGeneral procedure is not supported
1	scsiRequestInProgress	Parameter block request is in progress
1	shape_emptyType	An empty type doesn't have an area to draw
1	toggleOK	No error
2	[no name]	Disk in specified drive is already mounted
2	opNotImpl	Requested PrGeneral opcode not implemented in the current printer driver
2	scCommErr	Communications error, operation timeout
2	shape_inverse_fullType	An inverse full type doesn't have an area to draw
2	toggleBadField	Invalid field number
3	rectangle_zero_width	The rectangle doesn't have an area to draw
3	scArbNBErr	Bus busy, arbitration timeout

3	toggleBadDelta	Invalid delta value
4	rectangle_zero_height	The rectangle doesn't have an area to draw
4	scBadParmsErr	Bad parameter or unrecognized TIB instruction
4	toggleBadChar	Invalid character
5	polygon_empty	There is no contour to draw
5	scPhaseErr	Phase error on the SCSI bus
5	toggleUnknown	Unknown error
6	path_empty	There is no contour to draw
6	scCompareErr	Comparison error from <code>scComp</code> instruction
6	toggleBadNum	Tried to use character as number
7	bitmap_zero_width	The bitmap doesn't have an area to draw
7	scMgrBusyErr	SCSI Manager busy
7	toggleErr3	Reserved
7	toggleOutOfRange	Out of range (synonym for <code>toggleErr3</code>)
8	bitmap_zero_height	The bitmap doesn't have an area to draw
8	scSequenceErr	Attempted operation is out of sequence
8	toggleErr4	Reserved
9	scBusTOErr	Bus timeout during blind transfer
9	text_empty	There is no character to draw
9	toggleErr5	Reserved
10	glyph_empty	There is no glyph to draw
10	scComplPhaseErr	SCSI bus was not in status phase on entry to <code>SCSIComplete</code>
11	layout_empty	There is no layout to draw
12	picture_empty	There is no shape in the picture
13	shape_no_fill	The shape fill is set to <code>gxNoFill</code> , which will not draw
14	shape_no_enclosed_area	There is no enclosed area to draw
15	shape_no_enclosed_pixels	There is an enclosed area, but it is so small that it does not cross any pixel centers
16	shape_very_small	There is a shape to draw, but it is extremely small (on the order of the size of a pixel)
17	shape_very_large	Part of the shape may be drawn outside the bounds of the coordinate system ($\pm 32,768$)
18	shape_contours_cancel	The shapes contours overlap and cancel each other out
19	pen_too_small	The pen width is so small that it doesn't enclose any pixels and therefore doesn't draw
20	text_size_too_small	The text size is so small that it doesn't enclose any pixels and therefore doesn't draw
21	dash_empty	The dash shape was specified as an empty type shape
22	start_cap_empty	The start cap shape was specified as an empty type shape
23	pattern_empty	The pattern shape was specified as an empty type shape
24	textFace_Empty	Each layer of the text face has a shape fill equal to <code>gxNoFill</code>
25	shape_primitive_empty	The original shape enclosed an area; there is no stylized shape to draw; an example is a pattern shape that contains overlapping patterns that cancel

26	shape_primitive_very_small	There is a shape to draw, but it is extremely small (on the order of the size of a pixel)—an example is a scaled transform that shrinks the shape
27	transfer_equals_noMode	The transfer mode <code>gxNoMode</code> suppresses drawing
28	transfer_matrix_ignores_source	The transfer mode's mapping scales all values greater than 1 or less than 0 and the <code>overComponent</code> flag is not set
29	transfer_matrix_ignores_device	The transfer mode's mapping scales all values greater than 1 or less than 0 and the <code>overComponent</code> flag is not set
30	transfer_source_reject	The color is not within the source minimum and the source maximum
31	transfer_mode_ineffective	The transfer mode has no effect on the device—an example is a blend with an operand of 0
32	colorSet_no_entries	There are no colors in the color set so there is nothing to draw
33	bitmap_colorSet_one_entry	The bitmap drew, but it is probably not the desired result, since all colors map to the one color of the entry—an example is when the colors are off the end of the color set
34	transform_scale_too_small	The transform has reduced the shape to less than 1/72 inch—you may see a few pixels drawn, depending on the resolution of your view port
35	transform_map_too_large	The transform has moved all or part of the shape outside the bounds of the coordinate system
36	transform_move_too_large	The transform has moved all or part of the shape outside the bounds of the coordinate system
37	transform_scale_too_large	The transform has moved all or part of the shape outside the bounds of the coordinate system
38	transform_rotate_too_large	The transform has moved all or part of the shape outside the bounds of the coordinate system
39	transform_perspective_too_large	The transform has moved all or part of the shape outside the bounds of the coordinate system
40	transform_skew_too_large	The transform has moved all or part of the shape outside the bounds of the coordinate system
41	transform_clip_no_intersection	The clip shape does not intersect any view port
42	transform_clip_empty	The transform clip is an empty type shape
43	transform_no_viewPorts	The number of entries in the view port list is zero
44	viewPort_disposed	The view port that was to be drawn to has already been disposed of—there is no view port to draw to
45	viewPort_clip_empty	The view port clip is an empty type shape
46	viewPort_clip_no_intersection	The view port clip does not intersect the view device
47	viewPort_scale_too_small	The map to global space has been completed—the object is less than 1/72 inch; you may see a few pixels drawn, depending on the resolution of your view port
48	viewPort_map_too_large	The view port mapping has moved all or part of the shape outside the bounds of the coordinate system

49	viewPort_move_too_large	The view port mapping has moved all or part of the shape outside the bounds of the coordinate system
50	viewPort_scale_too_large	The view port mapping has moved all or part of the shape outside the bounds of the coordinate system
51	viewPort_rotate_too_large	The view port mapping has moved all or part of the shape outside the bounds of the coordinate system
52	viewPort_perspective_too_large	The view port mapping has moved all or part of the shape outside the bounds of the coordinate system
53	viewPort_skew_too_large	The view port mapping has moved all or part of the shape outside the bounds of the coordinate system
54	viewPort_viewGroup_offscreen	The shape is drawn to an off-screen view device—this may be normal; this error is returned to alert you in the event that the drawing result was unexpected
55	viewDevice_clip_no_intersection	The view device clip does not intersect the bounds described by the view device bitmap shape
56	viewDevice_scale_too_small	The mapping to global space has been completed—the object is less than 1/72 inch; you may see a few pixels drawn, depending on the resolution of your draw view port
57	viewDevice_map_too_large	The view device mapping has moved the shape outside the bounds of the coordinate system
58	viewDevice_move_too_large	The view device mapping has moved the shape outside the bounds of the coordinate system
59	viewDevice_scale_too_large	The view device mapping has moved the shape outside the bounds of the coordinate system
60	viewDevice_rotate_too_large	The view device mapping has moved the shape outside the bounds of the coordinate system
61	viewDevice_perspective_too_large	The view device mapping has moved the shape outside the bounds of the coordinate system
62	viewDevice_skew_too_large	The view device mapping has moved the shape outside the bounds of the coordinate system
128	iPrAbort	Application or user requested cancel
\$800008001	badComponentInstance	Invalid component passed to Component Manager; invalid component instance
\$800008002	badComponentSelector	Component does not support the specified request code